



AECG100

ECG, PPG, and PWTT Multifunction Tester

User Manual

Version 2026-07-20

AECG100 PC Software Version 1.0.10.40

Copyright © 2013-2026, All Rights Reserved.
WhaleTeq Co. LTD

No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language or computer language, in any form, or by any means, electronic, mechanical, magnetic, optical, chemical, manual or otherwise, without the prior written permission of WhaleTeq Co. LTD.

Disclaimer

WhaleTeq Co. LTD. provides this document and the programs "as is" without warranty of any kind, either expressed or implied, including, but not limited to, the implied warranties of merchantability or fitness for a particular purpose.

This document could contain technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in future revisions of this document. WhaleTeq Co. LTD. is under no obligation to notify any person of the changes.

The following trademarks are used in this document:




is a registered trademark of WhaleTeq Co. LTD

All other trademarks or trade names are property of their respective holders.

Contents

1	Product Introduction	9
2	System Setup.....	10
2.1	Product Appearance (AECG100 + Reflectance Modules)	10
2.2	Transmittance SpO ₂ module (PPG-2TF-660 2.0).....	13
2.3	Product Wiring Diagram.....	14
2.4	DUT Best Position Adjustment	17
2.4.1	Reflectance SpO ₂ Testing Device	17
2.4.2	Transmittance SpO ₂ Testing Device	18
2.5	Operation Modes.....	19
2.5.1	PC Software Operation	19
2.5.2	Standalone Operation.....	20
2.6	Reflectance PPG Module Fixture Mounting Base Dimensions	21
3	Software Installation	22
3.1	System Requirements	22
3.2	USB Driver Installation	22
3.3	Microsoft .Net Framework 4.0 Installation.....	23
4	Software Interface	24
4.1	General.....	24
4.1.1	PPG Configuration	24
4.1.2	Settings.....	26
4.1.3	Firmware Update.....	27
4.2	ECG Mode	29
4.3	PPG Mode.....	34
4.4	PWTT Mode	43
4.4.1	Download PhysioNet Database.....	47
4.5	Auto Test SpO ₂ Mode (will show after connecting the PPG-2TF-660 2.0)	50
4.6	SpO ₂ Mode.....	57
4.7	Auto Sequence Mode	66
4.8	Supported Raw Data File Format	67
5	Software Development Kit (SDK)	69
6	Calibration and Validation	69
6.1	Self-calibration	70
7	Troubleshooting.....	72
8	Cautions.....	73
9	Specification	74
9.1	ECG Test Mode	74
9.2	ECG Test Mode Parameters	75
9.3	PPG Test Mode (with Reflectance PPG Module).....	76
9.4	PPG Test Mode Parameters (with Reflectance PPG Module).....	77
9.5	PWTT Test Mode (with Reflectance and Transmittance PPG Module)	78

9.6	SpO ₂ Test Mode (with Reflectance PPG Module)	79
9.7	SpO ₂ Test Mode Parameters (with Reflectance PPG Module).....	80
9.8	PPG Test Mode Parameters (with Transmittance PPG Module)	81
9.9	SpO ₂ Test Mode (with Transmittance PPG Module).....	82
9.10	SpO ₂ Test Mode Parameters (with Transmittance PPG Module).....	83
9.11	Auto Test SpO ₂ Test Mode Parameters (with Transmittance PPG Module)	84
9.12	General Specification	84
10	Ordering Information.....	86
11	Package Contents.....	88
12	Revision History	90



List of Table

Table 1: Inverted/ Sync Pulse Function Description	41
Table 2: Inverted/Sync Pulse/Ambient Light Function Description	55
Table 3: Inverted/ Sync Pulse Function Description	64
Table 4: ECG Test Mode Specification	74
Table 5: ECG Test Mode Parameters	75
Table 6: PPG Test Mode Specification (with Reflectance PPG Module)	76
Table 7: PPG Test Mode Parameters (with Reflectance PPG Module)	77
Table 8: PWTT Test Mode Specification (with Reflectance and Transmittance PPG Module)	78
Table 9: SpO ₂ Test Mode Specification (with Reflectance PPG Module)	79
Table 10: SpO ₂ Test Mode Parameters (with Reflectance PPG Module)	80
Table 11: PPG Test Mode Parameters (with Transmittance PPG Module)	81
Table 12: SpO ₂ Test Mode Specification (with Transmittance PPG Module)	82
Table 13: SpO ₂ Test Mode Parameters (with Transmittance PPG Module)	83
Table 14: Auto Test SpO ₂ Test Mode Parameters (with Transmittance PPG Module)	84
Table 15: AECG100 Main Console Unit General Specification	84
Table 16: PPG Module General Specification	85
Table 17: AECG100 Main Console Unit Ordering Information	86
Table 18: PPG Module Ordering Information	86
Table 19: Optional Software Add-on Pack Ordering Information	87
Table 20: Optional Calibration Service and Warranty Extension Ordering Information	88
Table 21: AECG100 + PPG-1R-525 Package Contents	88
Table 22: AECG100 + PPG-2R-940 Package Contents	88
Table 23: AECG100 + PPG-2R-880 Package Contents	88
Table 24: AECG100 + PPG-2TF-660 2.0 Package Contents	89
Table 25: AECG100 Package Contents	89
Table 26: PPG-1R-525 Package Contents	89
Table 27: PPG-2R-940 Package Contents	89
Table 28: PPG-2R-880 Package Contents	89
Table 29: PPG-2TF-660 2.0 (30cm) Package Contents	90
Table 30: PPG-2TF-660 2.0 (60cm) Package Contents	90
Table 31: Revision History	90

List of Figure

Figure 1: Product Appearance (1).....	10
Figure 2: Set Mode A/B/C.....	11
Figure 3: Product Appearance (2).....	13
Figure 4: Direct Connection between AECG100 and PPG Module.....	14
Figure 5: Connection through DB15	14
Figure 6: Direct Connection between AECG100 and PPG-2TF-660 2.0.....	14
Figure 7: ECG Test Mode Product Wiring Diagram	15
Figure 8: ECG Test Mode with Noise Reduction Product Wiring Diagram.....	15
Figure 9: PPG Heart Rate Test Mode Product Wiring Diagram	15
Figure 10: Pulse Wave Transit Time Test Mode Product Wiring Diagram	16
Figure 11: SpO ₂ Test Mode Product Wiring Diagram	16
Figure 12: Auto Sequence Test Mode Product Wiring Diagram	16
Figure 13: Reflectance PPG-1R-525 Module (as example).....	17
Figure 14: Transmittance SpO ₂ Module (PPG-2TF-660 2.0)	18
Figure 15: Signal Detection.....	19
Figure 16: Fixture Mounting Base of PPG-1R Module.....	21
Figure 17: Fixture Mounting Base of PPG-2R modules	21
Figure 18: Sectional View	21
Figure 19: Button Functions in General Mode	24
Figure 20: PPG Configuration	24
Figure 21: Trigger level and Ambient light	25
Figure 22: AC above DC Illustration.....	25
Figure 23: AC below DC Illustration.....	25
Figure 24: Settings Function List.....	26
Figure 25: Firmware Update (Step 1)	27
Figure 26: Firmware Update (Step 2)	27
Figure 27: Firmware Update (Step 3)	28
Figure 28: Firmware Update (Step 4)	28
Figure 29: Firmware Update (Step 5)	29
Figure 30: ECG Mode Interface Buttons.....	29
Figure 31: Pacemaker Simulation Setting.....	30
Figure 32: ECG Respiration Setting.....	31
Figure 33: ECG Frequency Scan Setting.....	31
Figure 34: ECG Auto Heart Rate Testing Setting	31
Figure 35: Signal tab	32
Figure 36: Player Tab	32
Figure 37: Save Function	32
Figure 38: Load and Play Settings.....	33
Figure 39: PPG mode UI for PPG-1R-525 module	34
Figure 40: PPG mode UI for reflectance SpO ₂ module and transmittance SpO ₂ module.....	34
Figure 41: PPG Respiration and Modulation ^[1]	35
Figure 42: PPG Respiration Setting (with PPG-2R-880, PPG-2R-940 or PPG-2TF-660 2.0).....	37

Figure 43: PPG Respiration Setting (with PPG-1R-525)	37
Figure 44: PPG Database Player	38
Figure 45: Signal Tab.....	38
Figure 46: Sampling PD	38
Figure 47: Sampling LED Switch.....	39
Figure 48: Player Tab	39
Figure 49: Signal Tab.....	39
Figure 50: Sampling Tab: Sampling PD	39
Figure 51: Sampling Tab: Sampling LED Switch	40
Figure 52: Player Tab	40
Figure 53: Save Test Parameters	40
Figure 54: "Play/Apply" Button and "Stop" Button	41
Figure 55: Waveform Player	42
Figure 56: PWTT Mode UI for PPG-1R-525 module	43
Figure 57: PWTT mode UI for reflectance SpO ₂ module and transmittance SpO ₂ module	43
Figure 58: PWTT mode UI for PPG-1R-525 module.....	45
Figure 59: PWTT mode UI for reflectance SpO ₂ module and transmittance SpO ₂ module.....	45
Figure 60: Save Setting	46
Figure 61: Waveform Player Setting.....	47
Figure 62: "Database Player" Button.....	47
Figure 63: "PWTT Database Player" Window	48
Figure 64: Manually Download PhysioNet Database (step 2)	48
Figure 65: Manually Download PhysioNet Database (step 3)	49
Figure 66: Manually Download PhysioNet Database (step 4)	49
Figure 67: Manually Download PhysioNet Database (step 5)	50
Figure 68: Auto Trigger Level reminder.....	51
Figure 69: Auto Test SpO ₂ Interface	51
Figure 70: Auto Test SpO ₂ mode is operating	52
Figure 71: The DUT's DC values of R and IR appears.....	53
Figure 72: The DC value of R and AC and DC values of IR are automatically filled in	53
Figure 73: Fill in the AC value of R and the SpO ₂ value and save	54
Figure 74: The DUT's R curve.....	54
Figure 75: Signal Tab.....	54
Figure 76: Sampling PD	55
Figure 77: Sampling LED Switch.....	55
Figure 78: SpO ₂ mode UI for reflectance SpO ₂ module and transmittance SpO ₂ module	57
Figure 79: Setting R Curve	58
Figure 80: Using SpO ₂ Table	58
Figure 81: Equation for Obtaining the R Curve	58
Figure 82: Use Calibration Curve Function	59
Figure 83: Use Calibration Curve Interface	59
Figure 84: AC and DC Ratio.....	60
Figure 85: Using SpO ₂ Table	61

Figure 86: Build SpO ₂ Table (1)	61
Figure 87: Build SpO ₂ Table (2)	61
Figure 88: Automatic Calculation of the Intercept and Slope of the SpO ₂	61
Figure 89: Signal Tab.....	62
Figure 90: Sampling PD.....	62
Figure 91: Sampling LED Switch.....	62
Figure 92: Player Tab	62
Figure 93: Save Setting	63
Figure 94: Enter Activation Key Screen Display.....	63
Figure 95: "Play/Apply" Button and "Stop" Button	64
Figure 96: Waveform Player	65
Figure 97: Auto Sequence Mode	66
Figure 98: Add Waveform Files	66
Figure 99: AECG100 Interface Setup	70
Figure 100: Self-Calibration Setup.....	70
Figure 101: AECG100 $\pm 300\text{mV}$ DC offset.....	71
Figure 102: DC Voltage Verification (300mV).....	71
Figure 103: Self-Calibration Setup.....	72
Figure 104: DC Voltage Verification (>300mV).....	72

1 Product Introduction

WhaleTeq's AECG100 is a multifunction testing unit, which could function as ECG (Electrocardiogram) tester, PPG (Photoplethysmography) tester, PWTT (Pulse Wave Transit Time) tester, and SpO₂ (Peripheral Oxyhemoglobin Saturation) tester parameter adjustment control. The main ECG module is a single-lead ECG tester that could produce signals according to IEC standards for medical equipment. The users can use it with the single-channel or dual-channel PPG module of their choice. The single-channel PPG module provides a green LED, offering simulated PPG heart rate signals; besides, the dual-channel PPG module provides red LED and infrared LED, simulating different SpO₂ blood oxygen levels.

This tester also supports "4.3.1 PPG simulator test" of IEC 63203-402-3:2024.

When the ECG module and the PPG module work at the same time, the users can get the pulse wave transit time (PWTT) by adjusting the time difference (PTTp or PTTf) between the peak value of ECG to the peak or the valley of the PPG wave. The parameters can be used for improving the wearable devices on measuring blood pressure and calculating the degree of arteriosclerosis. This method can significantly increase the accuracy of the blood pressure measurement.

2 System Setup

2.1 Product Appearance (AECG100 + Reflectance Modules)

The left figure shows the AECG100 main console, the upper right figure shows the reflectance single-light module, and the lower right figure shows the reflectance SpO₂ module.

Figure 1: Product Appearance (1)



- (1) **AECG100 Main Console:** The ECG test module of the AECG100 Test System.
- (2) **PPG Fixture Mounting Base:** The fixture mounting base is provided for the user to develop the fixture to fasten DUT onto PPG modules of AECG100.
- (3) **LA/L Electrode:** Connect to DUT's matching electrode to output ECG signal.
- (4) **RA/R Electrode:** Connect to DUT's matching electrode to output ECG signal.
- (5) **RL2/N2 Electrode:** Connect to DUT's matching electrode.
- (6) **RL1/N1 Electrode:** Connect to DUT's matching electrode.
- (7) **AUX PWR Port:** Connect to a computer's USB port or a USB hub for power supply, and this USB port is not for data transferring. We strongly suggest connecting this USB port to prevent the power supply shortage.
- (8) **USB Port:** Connect to the computer's USB port for data transferring and power supply. If connect this USB port to a USB hub, AECG100 will operate in the standalone mode.
 Note: Please refer to "2.5.2 Standalone Operation" for more information.
- (9) **Power Switch:** To control power on and power off.
- (10) **Power Indicator:**

- Red LED remains on or no LED display: The AECG100 system is crashed and

needs further troubleshooting. Please see Chapter 7 Troubleshooting for further details.

- Red LED flashing: AECG100 is in standalone operation mode. The flash frequency is 1 time per second.
- Green LED flashing: AECG100 is in PC software operation mode. The flash frequency is 1 time per second.


(11) **GND Terminal:** In ECG test mode, we suggest putting a metal plate under AECG100 and DUT. Then, connect the AECG100 GND terminal and DUT ground to the metal plate to lower the noise. Please see section 2.3 for the set-up illustration.

(12) **Monitor Port:** The ECG output monitor port to enlarge the ECG signal for 1,000 times so that the user can measure via an oscilloscope.

(13) **Mode A/B/C LEDs:** To switch among 3 saved modes under standalone operations to output different signals. The LEDs light with corresponding modes.

- When AECG100 is connected to a computer, Mode A/B/C parameters can be saved via the Signal tab Standalone option of AECG100 PC software (see below figure).

Figure 2: Set Mode A/B/C



- Under standalone operation, the user can press the button to switch among the modes. There is a total of 3 modes to choose from, and only the LED light of the chosen mode will be on. The default mode is Mode A.
- Under standalone operation mode, switching modes require loading the restored parameters while LED flashes 4 times per second. The LED remains on when the restored parameters are loaded successfully.
- Mode A/B/C: The default parameters are for PWTT tests.

Note: When testing AECG100 main console with different PPG modules, re-

saving Mode A/B/C is required in order to obtain desired test results.

- (14) **Mode Selection Button:** To select amongst Mode A/B/C.
- (15) **DB15 Port (Female):** The port on the AECG100 main console to be connected with various PPG modules.
- (16) **DB15 Port (Male):** The port on the PPG module to be connected with that of (1)AECG100 main console.
- (17) **LED & Photodiode (PD):** Receiving the LED signal of DUT and emitting the LED signal to DUT.
- (18) **LED Monitor Port:** This is for the PPG-1R-525 PPG module to connect to the oscilloscope and measure the output voltage of the green LED AC signal. The output voltage is 100 times of original voltage.
- (19) **PD Monitor Port:** This is for the PPG-1R-525 PPG module to connect to the oscilloscope to measure electrical signal transferred by AECG100 PD. This port is for monitoring the optical signal of DUT's green LED.
- (20) **LED1 Monitor Port:** This is for the PPG-2R-880 or the PPG-2R-940 PPG module to connect to the oscilloscope and measure the output voltage of the red LED AC signal. The output voltage is 100 times of original voltage.
- (21) **PD1 Monitor Port:** This is for the PPG-2R-880 or the PPG-2R-940 PPG module to connect to the oscilloscope to measure electrical signal transferred by AECG100 PD. This port is for monitoring the optical signal of DUT's red LED.
- (22) **LED2 Monitor Port:** This is for the PPG-2R-880 or the PPG-2R-940 PPG module to connect to the oscilloscope and measure the output voltage of the infrared LED AC signal. The output voltage is 100 times of original voltage.
- (23) **PD2 Monitor Port:** This is for the PPG-2R-880 or the PPG-2R-940 PPG module to connect to the oscilloscope to measure electrical signal transferred by AECG100 PD. This port is for monitoring the optical signal of DUT's infrared LED.

2.2 Transmittance SpO₂ module (PPG-2TF-660 2.0)

Figure 3: Product Appearance (2)



- (1) **Index Finger Simulation:** To simulate the scenario of an index finger using an oximeter.
- (2) **EXT DB15 Connector:** To connect with AECG100 or the signal expander module.
- (3) **IR PD Monitor & Switch Port:**
 - **PD Monitor Port:** With this MCX to BNC port, PPG-2TF-660 2.0 can be connected to an oscilloscope to measure the optical signal sent by the infrared LED of the DUT to the PD.
 - **Switch Port:** With this MCX to BNC port, PPG-2TF-660 2.0 can be connected to an oscilloscope to display the switch status of infrared LED of PPG-2TF-660 2.0.
- (4) **R PD Monitor & Switch Port:**
 - **PD Monitor Port:** With this MCX to BNC port, PPG-2TF-660 2.0 can be connected to an oscilloscope to measure the optical signal sent by the red LED of the DUT to the PD.
 - **Switch Port:** With this MCX to BNC port, PPG-2TF-660 2.0 can be connected to an oscilloscope to display the switch status of red LED of PPG-2TF-660 2.0.
- (5) **USB-C Port:** Use the provided USB Type-C cable to connect PPG-2TF-660 2.0 to a power adapter, then plug the adapter into a power outlet.
- (6) **Signal Expander Module:** This module is only provided with the 60cm package and required for proper signal transmission. Do not remove.

2.3 Product Wiring Diagram

- Main Console and PPG Module Connection:
 - Directly connect with PPG module

Figure 4: Direct Connection between AECG100 and PPG Module



- Connect with PPG module with DB15

Figure 5: Connection through DB15



Figure 6: Direct Connection between AECG100 and PPG-2TF-660 2.0



- ECG Test Mode


Figure 7: ECG Test Mode Product Wiring Diagram



Note: When testing ECG only, the system will not be forced to connect with the reflectance module.

- ECG Test Mode with Noise Reduction Suggestion (see 2.1 (11) GND)

Figure 8: ECG Test Mode with Noise Reduction Product Wiring Diagram



- PPG Heart Rate Test Mode

Figure 9: PPG Heart Rate Test Mode Product Wiring Diagram



- Pulse Wave Transit Time Test Mode

Figure 10: Pulse Wave Transit Time Test Mode Product Wiring Diagram



- SpO₂ Test Mode

Figure 11: SpO₂ Test Mode Product Wiring Diagram



- Auto Sequence Test Mode

Figure 12: Auto Sequence Test Mode Product Wiring Diagram



2.4 DUT Best Position Adjustment

2.4.1 Reflectance SpO₂ Testing Device

Figure 13: Reflectance PPG-1R-525 Module (as example)



Step 1: Line up the DUT's LED with the PD of AECG100.

Step 2: Confirm the position of the DUT's LED and AECG100's PD are lined up: Connect AECG100 to the computer and power on AECG100. Download, install and execute the AECG100 software on the computer, and see if the pulse signals are visible on the PD's sampling tab. If so, the LED of the DUT is lined up with AECG100's PD.

Step 3: Confirm the positions of the DUT's PD and AECG100's LED: Execute the AECG100 software, and under PPG test mode, set DC=500mV AC=30mV BPM=60, and check if DUT can get the heart rate of 60 BPM.

- If so, then the relative positions of DUT's PD and AECG100's LED are correct.
- If not, try to modify the DC value by adding or reducing 50mV and check again to see if DUT can get the heart rate of 60. If the heart rate is still not found, reposition DUT and repeat Step 2 and Step 3 until DUT can get the heart rate.

2.4.2 Transmittance SpO₂ Testing Device

Figure 14: Transmittance SpO₂ Module (PPG-2TF-660 2.0)



Step 1: Clamp the DUT to the index finger simulation on the PPG-2TF-660 2.0, and plug the DB15 connector on the PPG-2TF-660 2.0 into the DB15 port on the AECG100 main console.

Note: Align the LED and PD on DUT to the PD and LED on the PPG-2TF-660 2.0 respectively.

Step 2: Connect the PPG-2TF-660 2.0 to a power adapter using the provided USB Type-C cable, then plug the power adapter into a power outlet.


Note:

1. When using the PPG-2TF-660 2.0, do not connect other devices to the power adapter if it is equipped with multiple USB Type-C ports.
2. The power adapter must support USB Power Delivery (USB PD). The required charging specification for the PPG-2TF-660 2.0 is 9V / 2A; therefore, the USB PD capability must support at least 18W.

Step 3: Plug the USB Type-B connectors of the USB cables provided to the AUX PWR port and USB port on the AECG100 main console; at the other end of the USB cables, plug the USB Type-A connectors into a laptop or a PC. Switch the power switch located at the lower-left corner on the top of the AECG100 main console to "On" to power on it.

Step 4: Go to the [official AECG100 webpage](#) to download and install the AECG100 software. Complete the installation and click the AECG icon to start the test. Select the Auto Test SpO₂ tab and check the "signal strength" on the software interface. It shows the optical signal intensity detected.

Figure 15: Signal Detection



Note: Because the light intensity of the DUT varies, the "signal strength" may not be filled. Please adjust the position and find a relatively large signal value.

2.5 Operation Modes

AECG100 can be controlled through PC software operation or standalone operation.

2.5.1 PC Software Operation

AECG100 must be connected to the computer and the PC software should be installed properly. AECG100 offers a total of 4 test modes, including ECG test mode, PPG test mode, PWTT test mode, and SpO₂ test mode. Auto Sequence test mode can combine any of the 4. Please see chapter 4 Software Interface for a detailed operation description.

- **ECG Test Mode:** AECG100 can conduct single-lead ECG testing under this test mode. All the ECG-related standards are supported including a series of single-channel testing, such as sensitivity, frequency response, input impedance, and so on. This test mode is compliant with international standards of IEC 60601-2-47, YY 0885, and YY 9706.247.
- **PPG Mode:** Users can choose different testing waveforms and adjust waveform parameters under this test mode. To test the PPG heart rate accuracy of the DUT, AECG100 can simulate human skin reflection signals and noise. Moreover, users can record or program a set of signals, and play the signals using this test mode. It is a very useful tool when developing the algorithm.
- **PWTT Mode:** The device can send ECG and PPG signals simultaneously under this test mode. By adjusting the time difference of the two signals, users can

improve the blood measurement algorithm of wearable devices or calculate the degree of arteriosclerosis.

- Auto Test SpO₂ Mode: Apply only to PPG-2TF-660 2.0 module. When PPG-2TF-660 2.0 detects the signals from the DUT, the system will identify the parameter settings such as Trigger Level and DC value of R/IR, and record Trigger Level to SpO₂ and PPG tabs. Users can adjust the pulse amplitude, transmission rate, ambient light value and quick verification.

Note:

1. This mode is mainly for developers to quickly test for reference, not for after-sales calibration and testing on oximeters. If users require development tests on SpO₂ parameters and specifications, please use the SpO₂ mode.
2. If the DUT can't measure the SpO₂ value or its SpO₂ measured value fluctuates, please adjust the measuring position or select another transmission rate to test. At the same time, checking the human body detection algorithm of the DUT is suggested.

If further assistance is needed, please contact WhaleTeq.

- SpO₂ Mode: Under this test mode, users can individually adjust the AC/DC ratio of R and IR LED. This is to simulate the light absorption degree so that DUT can determine the SpO₂ value after receiving AECG100's optical signals.
- Auto Sequence Mode: User can program a playlist including play time and sequence of different waveforms. The playlist can be saved as a file for repeated playback. Users can save a significant testing time of switching among different waveforms and parameters.

2.5.2 Standalone Operation


Up to 3 quick test modes can be stored in AECG100. This is designed for quick testing without opening AECG100's PC software. A USB hub can be used as a power source.

2.6 Reflectance PPG Module Fixture Mounting Base Dimensions

Below are the dimensions of PPG module fixture mounting base. User can develop a fixture to fasten DUT onto the PPG module fixture mounting base. AECG100 3D Model can be downloaded [here](#).


- Mechanical Drawing (Fixture mounting base of PPG-1R Module)

Figure 16: Fixture Mounting Base of PPG-1R Module




- Mechanical Drawing (Fixture mounting base of PPG-2R modules)

Figure 17: Fixture Mounting Base of PPG-2R modules



- Sectional View:

Figure 18: Sectional View



3 Software Installation

3.1 System Requirements

AECG100 Test System uses a Windows PC to connect and control the USB module of AECG100 unit.

PC requirements:

- Windows PC (Windows 7 or later, suggest to use the genuine version)
- Microsoft .NET 4.0 or higher
- Administrator access (essential for installing software, driver, and Microsoft .Net Framework)
- 1.5 GHz CPU or higher
- 1GB RAM or higher¹
- USB port

Note: If this is the first time using WhaleTeq's product, please refer to the two sections below (3.2 and 3.3) to confirm that the USB driver and Microsoft .Net Framework 4.0 are both installed.

3.2 USB Driver Installation

If Windows device manager can't recognize WhaleTeq's product, please follow the below instructions to Install Microchip® USB driver.

Microsoft Windows 10

- As Windows 10 has built-in Microchip® USB Driver, there are no needs to install any drivers. It just takes a while for Windows Device manager to recognize and install the driver.

Microsoft Windows 8 and Windows 8.1

¹ Relative to normal PC processing, there is no special use of PC speed. However, there has been noted a slow increase in system RAM usage over long periods of time up to 30-40MB (related to MS Windows "garbage collection"). PCs with only 512MB or less installed and are running several other programs (in particular, Internet Explorer), may exceed the available RAM, requiring access to the hard drive and dramatically impacting speed. In this case, streaming interruptions and other problems may occur.

- If Windows 8 and Windows 8.1 can't recognize AECG unit, please download "[mchpcdc.inf](#)" from WhaleTeq website. This driver is provided by Microchip® to be used with PIC microprocessors having built-in USB function.
- As mchpcdc.inf provided by Microchip® does not contain digital signature, please disable driver signature enforcement in Windows 8 and Windows 8.1. Please click [here](#) to watch the tutorial video.
- When the USB module is connected for the first time, select manual installation, and point to the folder containing the above file. Then continue to follow the instructions to finish the installation. There may be a warning that the driver is not recognized by Windows®, and this can be ignored. Please click [here](#) to watch the tutorial video.

Microsoft Windows 7

- If Windows 7 can't recognize AECG100 unit, please download "[mchpcdc.inf](#)" from WhaleTeq website. This driver is provided by Microchip® to be used with PIC microprocessors having built-in USB function.
- When the USB module is connected for the first time, select manual installation, and point to the folder containing the above file. Then continue to follow the instructions to finish the installation. There may be a warning that the driver is not recognized by Windows®, and this can be ignored. Please click [here](#) to watch the tutorial video.

3.3 Microsoft .Net Framework 4.0 Installation

WhaleTeq software is developed based on Microsoft .Net Framework 4.0. If AECG software fails to execute properly, please check whether Microsoft .Net Framework 4.0 or higher versions was installed in the operation system.

If your PC hasn't installed Microsoft .Net Framework 4.0 or higher versions, please download from Microsoft website. Please click [here](#) to watch the tutorial video (from 2:03).

4 Software Interface

4.1 General


Figure 19: Button Functions in General Mode



4.1.1 PPG Configuration


This function belongs to the PPG module and configures PWTT, SpO₂, PPG, and Auto Sequence (where applicable) tabs. Different DUTs might have different signal processing, so AECG100 provides the “Inverted” function to output the inverted waveform, which can be confirmed on an oscilloscope. Check “Synchronized Pulse” to enable the synchronization behavior between AECG100 LED and DUT LED.

Figure 20: PPG Configuration




- **Trigger level:** Set the trigger level that drives the AECG100 LED to turn on after the AECG100 PD detects the value of the LED brightness of the DUT.
- **Ambient light:** Available when connecting the transmittance SpO₂ module PPG-2TF-660 2.0 to the AECG100 main console to superimpose 14 types of simulated indoor/outdoor ambient light signals to the output waveform.

Figure 21: Trigger level and Ambient light



- **AC above DC:** Configures the AECG100 to output the AC signal above the DC signal.

Figure 22: AC above DC Illustration




- **AC below DC:** Configures the AECG100 to output the AC signal below the DC signal. This is the default setting at power-on.

Note:

1. After setting "AC above DC" or "AC below DC", the AECG100 saves the selected setting and applies it at the next power-on.
2. When "AC below DC" is selected, the DC value will change as the AC value increases, even if the "Lock DC" function is enabled.

Example: If the initial red-light AC value is 40.33 and the DC value is 340, and the "Lock DC" function is enabled, increasing the AC value to 43.33 will cause the DC value to change to 343 accordingly.

Figure 23: AC below DC Illustration




4.1.2 Settings

Applies to all tabs unless specified otherwise.

- Select “Check for Updates” to ensure whether there are software or firmware updates.
- Select “Help” to see the instruction of the SpO₂ table and WhaleTeq file format.
- Select “Language” to switch among English, simplified Chinese, and traditional Chinese.
- Select “Restore Factory Settings” to reset the following back to default settings: LED Level of PWTT, SpO₂, and PPG tabs, and Trigger level from *Sampling* of SpO₂ and PPG tabs.
- Select “Device Information” to check the device serial number.
- Select “License” to confirm AECG100 device ID and check the activation status of ECG standard assistant software and PPG/ PWTT database player.
- Select “About” to check the software version and device function introduction.

Figure 24: Settings Function List




4.1.3 Firmware Update

Please follow the steps below to update firmware.


Step 1: Click the setting button in the upper-right corner and select “About”.

Figure 25: Firmware Update (Step 1)



Step 2: Click “Update F/W”.


Figure 26: Firmware Update (Step 2)



Step 3: Select the file for updating firmware or FPGA, then click “Open”.


Note: The screenshot below shows a file for updating FPGA.

Figure 27: Firmware Update (Step 3)




Step 4: Click “Yes” to activate the update.

Figure 28: Firmware Update (Step 4)



Step 5: The update is processing. After it's complete, please reboot the AECG100 for use.

Figure 29: Firmware Update (Step 5)




4.2 ECG Mode

ECG Mode can be separated into 2 sections. The upper section is for waveform selection and test parameter setting; the lower section is for waveform playback display and setting.


Upper section:

Figure 30: ECG Mode Interface Buttons




- (1) **BPM:** Adjust for different BPM (Beat-Per-Minute).
- (2) **Output Electrode Selection:** Choose the output electrode.
 - RA/R: Right Arm Electrode
 - LA/L: Left Arm Electrode
- (3) **Output Waveform Selection:** Select to output different waveform types (ex. Sine, Triangle, Square...).
- (4) **Output Waveform Parameter:** Adjust voltage and time parameters of standard waveforms and pulse waveforms.
- (5) **Noise Simulation:** To simulate noise with different frequency and amplitude.
- (6) **DC Offset (DC Fine-tune):** To add a DC offset of +300mV, 0 or -300mV to the output signal.
- (7) **Input Impedance Test:** To add 620k Ω / 4.7nF to the output signal. This is for ECG DUT to measure the amplitude and evaluate the input impedance of ECG DUT.
- (8) **Pacemaker:** Output simulated ECG pacemaker signal to ECG DUT.

Figure 31: Pacemaker Simulation Setting



- (9) **RLD:** Right Leg Detection for measurement of reference voltage difference of DUT.
- (10) **Respiration:** AECG100 uses the impedance pneumography method to simulate the impedance changes of human skin when breathing. "Respiration Rate" is the number of breaths taken during 60 seconds intervals. "Basic Level" refers to the impedance of human skin, and "Variations" refers to the impedance changes while breathing. Respiration "Ratio" is the ratio of inhalation to exhalation. The "Apnea Selection" consists of "Duration" (apnea length) and "Cycle" (regular breathing time). Please note that "Duration" (apnea length) is not included in "Cycle" (regular breathing time).

Figure 32: ECG Respiration Setting



ECG Respiration

☒ Enable

Respiration

Respiration Rate: 20 BrPM

Basic Level: 1000 Ω

Variations: 1.0 Ω

Ratio 1: 1

☒ Apnea Selection


Duration: 10 sec

Cycle: 1 min

OK Cancel

- (11) **Frequency Scan:** Users can set the amplitude, start frequency, stop frequency, and duration. This function is for testing the frequency response of ECG DUT by using the sine wave.

Figure 33: ECG Frequency Scan Setting



ECG Frequency Scan (Sine)

Amplitude: 1.00 mV

Start: 0.67 Hz


Stop: 150.00 Hz

Duration: 30 s

Start

- (12) **Std. Assistant software:** Standard assistant software supports international medical standards of IEC 60601-2-47, YY 0885, and YY 9706.247. It simplifies the standards into test parameters, test criteria, and test sequences. This is an optional function, please contact WhaleTEQ for detailed information and purchase.
- (13) **Auto Heart Rate:** By using the ECG waveform, the auto heart rate function can set different test combinations of BPM, QRS Amplitude, QRS duration, and interval.

Figure 34: ECG Auto Heart Rate Testing Setting



ECG Auto Heart Rate Testing

Select All None

Heart Rate (BPM) ☒ 30 ☒ 60 ☒ 120 ☒ 180 ☐ 200

QRS Amplitude (mV) ☒ 0.5 ☒ 1 ☒ 2 ☒ 5

QRS Duration (ms) ☐ 40 ☒ 70 ☐ 80 ☒ 100 ☒ 120

Interval (s) 30


Start

Lower section:

* The UI is illustration only. For detailed display please check on oscilloscope.

- (1) **Signal tab:** Users can reset/ save/ recall/ play waveform with preset parameters.

Figure 35: Signal tab




- (2) **Player tab:** Users can load/ play/ loop raw data file.

Figure 36: Player Tab



- (3) **Reset:** Resume the default setting in the upper section.
- (4) **Save:** Save the preset test parameters from the upper section into Standalone (device Mode A/B/C), PC file (in *.ecg), or Waveform Raw (in *.txt) format.

Figure 37: Save Function




Note: Standalone (device Mode A/B/C) and PC file can be used in (1) Signal tab "Recall" and Auto Sequence Mode. Only Waveform Raw can be played in (2)

Player tab.

- (5) **Recall:** Load the previously saved test parameters stored in Standalone (device Mode A/B/C) or as a PC file (*.ecg format).
- (6) **Play/ Stop:** Play the selected waveform with preset parameters. Once stopped, play from the beginning.
- (7) **Waveform Display Scale:** Adjust the display scale for 5mm/mV, 10mm/mV, or 20mm/mV.
- (8) **Display Window Enlargement:** Click to enlarge the display window.
- (9) **Load:** User can load and play raw data via selecting the raw data file either saved from (1) Signal tab “Waveform Raw” or self-constructed according to WhaleTeq rule (click “Help” for more details). The total length shows the total playback time of raw data.

Figure 38: Load and Play Settings



- (10) **Play/ Stop:** Play the selected raw data file in *.txt format. Once stopped, play from beginning.
- (11) **Loop:** Check to replay the raw data file repeatedly.
- (12) **Current Position:** Display the timing of the played raw data.


4.3 PPG Mode

It requires to connect PPG-1R-525, PPG-2R-880, PPG-2R-940 or PPG-2TF-660 2.0 module to initiate PPG test mode. PPG Mode can be separated into 2 sections. The upper section is for waveform selection and test parameter setting; the lower section is for waveform playback display and setting.

Upper section:


The software UI is for AECG100 main console unit with PPG-1R-525 module

Figure 39: PPG mode UI for PPG-1R-525 module




The PPG mode UI is for AECG100 main console unit with reflectance SpO₂ module (PPG-2R-880/PPG-2R-940)/transmittance SpO₂ module (PPG-2TF-660 2.0)

Figure 40: PPG mode UI for reflectance SpO₂ module and transmittance SpO₂ module



- (1) **BPM:** Adjust for different heart rates. The value is from 10 BPM to 300 BPM.
- (2) **Output Waveform Parameter:** Adjust voltage and time parameters of standard waveforms and pulse waveforms.
- (3) **Output Waveform Selection:** Select to output different waveform types (ex. PPG, Sine, Triangle, Square...).
- (4) **Noise Simulation:** To simulate noise with different frequency and amplitude.
- (5) **PPG Config:** Refer to 4.1 General 4.1.1 PPG Configuration.
- (6) **Setting:** Refer to 4.1 General 4.1.2 Settings.
- (7) **Respiration:** Add respiration modulation to the PPG function. Baseline Modulation (BM), Pulse Amplitude Modulation (AM), and Frequency Modulation (FM) are the available signals for breath modulation.
 - i. **Baseline Modulation (BM):** Change in intrathoracic pressure when breathing causes changes in venous blood return, which changes the baseline of PPG ^[1]. Also called DC modulation.
 - ii. **Pulse Amplitude Modulation (AM):** The heart axis deviates when breathing. Inspiration corresponds to decreased left ventricular (the main pumping chamber) stroke volume, which leads to decreased pulse amplitude ^[1].
 - iii. **Frequency Modulation (FM):** As a result of autonomic nervous system activity fluctuation, breathing leads to changes in heartbeats ^[2]. Pulse period varies over the respiratory cycle: Heart rate increases during inspiration; decreases, expiration. Also known as RSA (respiratory sinus arrhythmia) ^[3].

Figure 41: PPG Respiration and Modulation ^[1]



a) Unmodulated waveform; b) Baseline; c) Amplitude; d) Frequency

¹ Addison, P.S., Watson, J.N., Mestek, M.L. *et al.* Developing an algorithm for pulse oximetry derived respiratory rate (RR_{oxi}): a healthy volunteer study. *J Clin Monit Comput* **26**, 45–51 (2012). <https://doi.org/10.1007/s10877-011-9332-y>

² Addison, P.S., Watson, J.N., Mestek, M.L. *et al.* Pulse oximetry-derived respiratory rate in general care floor patients. *J Clin Monit Comput* **29**, 113–120 (2015). <https://doi.org/10.1007/s10877-014-9575-5>

³ Paul S. Addison. Respiratory effort from the photoplethysmogram. *Medical Engineering & Physics* **41**, 9–18 (2017). <https://doi.org/10.1016/j.medengphy.2016.12.010>.

Users can choose the appropriate modulation signal with different parameters (respiration rate, inhale/ exhale ratio, and variation range) to conduct the signal simulation.

- “Respiration Rate” is the number of breaths taken during 60 seconds intervals, ranging from 1 to 150 BrPM.
- Respiration “Ratio” is the ratio of inhalation to exhalation, up to 1:5.
- “Variation” adjustment ranges -16 ~ 16%. BM refers to the baseline drift of the PPG amplitude during one breathing cycle, with baseline drift ranging from -16 to 16%. In the contrast, AM means that the amplitude itself of the PPG wave changes -16 ~ 16% of the original amplitude during one breathing cycle. FM shifts the pulse duration instead of amplitude: in one breathing cycle, the interval change between the heartbeat is -16 ~ 16% of the original set heartbeat.

The adjustment method is shown in the figures below.

Note: The PPG respiration signal multiple selection function of BM, AM, and FM in software version 1.0.9.4 must be used with firmware version 1.15.02.14. If a waveform saved using a previous software version contains respiration parameter settings, it must be re-saved with all parameter settings due to compatibility issues before it can be played back.

Figure 42: PPG Respiration Setting (with PPG-2R-880, PPG-2R-940 or PPG-2TF-660 2.0)






Figure 43: PPG Respiration Setting (with PPG-1R-525)



- (8) **Database Player:** The WhaleTeq database includes 30 records of PPG waveforms recorded in clinical trials to be used in PPG test mode and 10 records of PPG and ECG waveforms recorded in clinical trials to use in PWTT test mode. The recorded disease waveforms, including AF (Atrial Fibrillation), APC (Atrial Premature Complexes), VPC (Ventricular Premature Contraction), and first-degree AV block. The first record is available for trial purpose and illustrated in Player tab from the lower section. Please contact WhaleTeq to purchase the completed database playback function.

Figure 44: PPG Database Player



- (9) **R/IR Test Parameter Selection:** Click to see settings of Red LED or Infrared LED.

Lower section:

The software UI is for AECG100 main console unit with PPG-1R-525 module

** The UI is illustration only. For detailed display please check on oscilloscope.*


Signal Tab

Figure 45: Signal Tab




Sampling Tab: Sampling PD

Figure 46: Sampling PD




Sampling Tab: Sampling LED Switch

Figure 47: Sampling LED Switch



Player Tab

Figure 48: Player Tab



The PPG mode UI is for AECG100 main console unit with reflectance SpO₂ module (PPG-2R-880/PPG-2R-940)/transmittance SpO₂ module (PPG-2TF-660 2.0)

* The UI is illustration only. For detailed display please check on oscilloscope.


Signal Tab

Figure 49: Signal Tab




Sampling Tab: Sampling PD

Figure 50: Sampling Tab: Sampling PD



Sampling Tab: Sampling LED Switch

Figure 51: Sampling Tab: Sampling LED Switch




Player Tab

Figure 52: Player Tab



- (1) **Signal tab:** Users can reset/ save/ recall/ play waveform with preset parameters.
- (2) **Sampling tab for PD/LED Switch:** Users can observe DUT LED brightness and AECG100 LED switch status.
- (3) **Player tab:** Users can load/ play/ loop raw data file.
- (4) **Reset:** Resume the default setting in the upper section.
- (5) **Save:** Save the preset test parameters from the upper section into Standalone (device Mode A/B/C), PC file (in *.ppg), or Waveform Raw (in *.txt) format.


Figure 53: Save Test Parameters



Note: Standalone (device Mode A/B/C) and PC file can be used in (1) Signal tab “Recall” and Auto Sequence Mode. Only Waveform Raw can be played in (3) Player tab.

- (6) **Recall:** Load the previously saved test parameters stored in Standalone (device Mode A/B/C) or as a PC file (*.ppg format).
- (7) **Play/Apply:** Play the selected waveform with preset parameters. After clicking “Play”, the button changes to “Apply”. Parameters can be adjusted during waveform playback. Click “Apply” to output the waveform using the new settings.
To stop playback, click the Stop button () next to the PPG tab.

Figure 54: “Play/Apply” Button and “Stop” Button



- (8) **Waveform Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec time frames.
- (9) **Inverted/Sync Pulse:**

Table 1: Inverted/ Sync Pulse Function Description

Inverted: On	AECG100 outputs PPG waveform upside down.
Inverted: Off	AECG100 output PPG waveform as per the window display.
Sync Pulse: On	LED behaviors of AECG100 synchronize with DUT LED.
Sync Pulse: Off	AECG100 LED remains on.

- (10) **Sampling:** To sample and measure the DUT LED brightness.
- (11) **Signal:**

PD-Green/ PD-RED/ PD-Infrared:

It shows the intensity and behaviors of DUT LED sampled by AECG100’s PD. Displayed

in **Blue** and **Purple** curves.


Switch-Green/ Switch-RED/ Switch-Infrared:

It shows the timing AECG100 switches LED on or off. Waveform displays low means AECG100 turn on LED. Waveform displays high means AECG100 turns off LED. Displayed in **Blue** and **Red** curves.

PD/ Switch selection is memorized.

- (12) **Freeze:** Once checked, the display of PD/ LED switch sampling would stay as it is.
- (13) **Max Peak:** Display the peak value of DUT LED, which is sampled by AECG100 PD, during the selected time interval.
- (14) **Time axis:** Adjust to change the unit of the time axis.
- (15) **Enlarge:** Click to better view the sampling details.
- (16) **Load:** It requires loading PPG raw data separately by different “Channels” (PPG Green/ PPG RED/ PPG Infrared). The raw data file can be loaded by clicking the “File” section. The raw data file is either saved from (1) Signal tab “Waveform Raw” or self-constructed according to the WhaleTeq rule (click “Help” for more details). The “Signal” number corresponds to channel types. The “Total Length” displays the total playback time. Users have to manually adjust “Output Setting” to ensure the AECG100 output signal properly.

Figure 55: Waveform Player



- (17) **Play/Stop:** Play the selected raw data file in *.txt format. Once stopped, play from the beginning.
- (18) **Loop:** Check to replay the raw data file repeatedly.
- (19) **Current Position:** Display the timing of the played raw data.
- (20) **Waveform Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec time frames.
- (21) **Output Selection:** Users can select to play signals via RED LED (waveform displayed in **Grey-green**) and Infrared LED (waveform displayed in **Purple**), or via either one of them.


4.4 PWTT Mode

It requires to connect Green LED PPG module (PPG-1R-525) or reflectance SpO₂ module (PPG-2R-840/PPG-2R-940) or transmittance SpO₂ module (PPG-2TF-660 2.0) to initiate PWTT test mode. PWTT Mode can be separated into 2 sections. The upper section is for waveform selection and test parameter setting; the lower section is for waveform playback display and setting.

Upper section:


The software UI is for AECG100 main console unit with PPG-1R-525 module

Figure 56: PWTT Mode UI for PPG-1R-525 module



The PWTT mode UI is for AECG100 main console unit with reflectance SpO₂ module (PPG-2R-880/PPG-2R-940)/transmittance SpO₂ module (PPG-2TF-660 2.0)

Figure 57: PWTT mode UI for reflectance SpO₂ module and transmittance SpO₂ module



- (1) **Electrode:** Select the output electrode to RA/R or LA/L.
- (2) **ECG Waveform Parameter:** Set test parameters of voltage and time.
- (3) **BPM:** Adjust different heart rates for testing.

- (4) **Sync BPM:** BPM values of ECG wave and PPG wave are locked to be synchronized.
- (5) **Load ECG Mode Waveform:** Load and display ECG mode preset waveform.
- (6) **Load PPG Mode Waveform:** Load and display PPG mode preset waveform. Not allowed when PPG BPM differs from that of ECG's.
- (7) **PPG Waveform Parameters:** PPG waveform can be adjusted via PI (Perfusion Index) = AC/DC. Select "Lock AC" to adjust DC and PI values. Select "Lock DC" to adjust AC and PI values.
- (8) **Time Difference:** Adjust the time difference between ECG (R wave peak) and PPG waveform (peak or trough). PTTp is the time to peak and PTTf is the time to trough.
- (9) **Database Player:** In PWTT test mode, AECG100 can download and play PhysioNet MIMIC database (mimicdb). Furthermore, the WhaleTeq database includes 30 records of PPG waveforms recorded in clinical trials to use in PPG test mode and 10 records of PPG and ECG waveforms recorded in clinical trials to use in PWTT test mode. The recorded PPG disease waveforms include AF (Atrial Fibrillation), APC (Atrial Premature Complexes), VPC (Ventricular Premature Contraction), and first-degree AV block. Additional 5 records of AF (Atrial Fibrillation) are provided for PWTT test mode. The first record is available for trial purposes and illustrated in the Player tab from the lower Section. Please contact WhaleTeq to purchase the completed database playback function.
- (10) **Respiration:** Add respiration modulation to the PPG function. Baseline Modulation (BM), Pulse Amplitude Modulation (AM), and Frequency Modulation (FM) are the available signals. Please refer to "[\(8\) Respiration](#)" in the "4.3 PPG Mode" for more information.
- (11) **Auto PWTT:** Set time difference, PTTp range, PTTp step, and intervals for PWTT automation.
- (12) **R/IR Selection:** Click to switch between RED and IR LED test parameters page.

Lower section:

The software UI is for AECG100 main console unit with PPG-1R-525 module

** The UI is illustration only. For detailed display please check on oscilloscope.*

Figure 58: PWTT mode UI for PPG-1R-525 module



The PWTT mode UI is for AECG100 main console unit with reflectance SpO₂ module (PPG-2R-880/PPG-2R-940)/transmittance SpO₂ module (PPG-2TF-660 2.0)

** The UI is illustration only. For detailed display please check on oscilloscope.*


Figure 59: PWTT mode UI for reflectance SpO₂ module and transmittance SpO₂ module



- (1) **Signal tab:** Users can reset/ save/ recall/ play waveform with preset parameters.
- (2) **Player tab:** Users can load/ play/ loop raw data file.

- (3) **Reset:** Resume the default setting in the upper section.
- (4) **Save:** Save the preset test parameters from the upper section into Standalone (device Mode A/B/C), PC file (in *.pwv), or Waveform Raw (in *.txt) format.


Figure 60: Save Setting



Note: Standalone (device Mode A/B/C) and PC file can be used in (1) Signal tab “Recall” and Auto Sequence Mode. Only Waveform Raw can be played in (2) Player tab.

- (5) **Recall:** Load the previously saved test parameters stored in Standalone (device Mode A/B/C) or as a PC file (*.pwv format).
- (6) **Play/ Stop:** Play the selected waveform with preset parameters. Once stopped, play from the beginning.
- (7) **Output waveform selection:** Select to play ECG waveform (displayed in **Blue**) and/ or PPG waveform.
- (8) **Waveform Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec time frames.
- (9) **Load:** It is required to load PPG/ ECG raw data separately by different “Channels” (ECG/ PPG Green/ PPG RED/ PPG Infrared). Either saved from (1) Signal tab “Waveform Raw” or self-constructed according to WhaleTeq rule (click “Help” for more details), the raw data file can be loaded by clicking the “File” section. The “Signal” number corresponds to channel types. The “Total Length” displays the total playback time. Users have to manually adjust “Output Setting” to ensure AECG100 outputs signal properly.

Figure 61: Waveform Player Setting



(10) **Play/Stop:** Play the selected raw data file in *.txt format. Once stopped, play from the beginning.

(11) **Loop:** Check to replay the raw data file repeatedly.


(12) **Current Position:** Display the timing of the played raw data.

Note: If the transmittance SpO₂ module has ECG function, the PWTT mode operation is the same as the above.

4.4.1 Download PhysioNet Database


1. Click the "Database Player" button to open the "PWTT Database Player" window.

Figure 62: "Database Player" Button



2. Select “MIMIC Database (mimicdb)” and choose the desired “Record” and file. Then click the “Download” button, the AECG100 will automatically connect to the PhysioNet website to download the data.


Figure 63: “PWTT Database Player” Window



If a “Download File Failed” message appears, please follow these steps to manually download the data:

- (1) Visit <https://physionet.org/content/mimicdb/1.0.0/#files-panel> to access the files.
- (2) Select the desired folder.

Figure 64: Manually Download PhysioNet Database (step 2)




(3) Download the “.abp” and “.hea” files, and the desired “.dat” and “.hea” files as well. Note: The “.abp” and “.hea” files belong to the selected folder and only need to be downloaded once.

Other “XXX00XXX” files represent different raw data sets. Please download the “.dat” and


“.hea” files as needed.

Figure 65: Manually Download PhysioNet Database (step 3)




(4) Save the downloaded files to the “C:\Users\

Figure 66: Manually Download PhysioNet Database (step 4)



(5) Return to the “PWTT Database Player” window of AECG100 and click the “Download” button to complete the download.

Figure 67: Manually Download PhysioNet Database (step 5)


4.5 Auto Test SpO₂ Mode (will show after connecting the PPG-2TF-660 2.0)

This mode can automatically identify the parameter settings such as Trigger Level and the DC values of R/IR (the AC value of IR can be displayed when using the "Table" function on this tab to create an R curve).

The Trigger Level will be recorded to SpO₂ and PPG tabs to help users quickly perform tests; the DC values of R/IR provide the light intensity information of themselves emitted by the DUT.

Note:

1. This mode is mainly for developers to quickly test for reference, not for after-sales calibration and testing on oximeters. If users require development tests on SpO₂ parameters and specifications, please use the SpO₂ mode.
 2. If the DUT can't measure the SpO₂ value or its SpO₂ measured value fluctuates, please adjust the measuring position or select another transmission rate to test. At the same time, checking the human body detection algorithm of the DUT is suggested.
- If further assistance is needed, please contact WhaleTeq.

The Auto Test SpO₂ Mode is only applicable to the PPG-2TF-660 2.0. The PPG-2TF-660 2.0 can be used only after it is connected to the AECG100.


If the Auto Trigger Level reminder shows, please check the IR status, or whether the DUT connects to the PPG-2TF-660 2.0 and is in a proper measuring position. After confirming the aforementioned situations, click "OK" to continue.

Figure 68: Auto Trigger Level reminder



Auto Test SpO₂ Mode tab can be separated into 2 sections. The upper section is for waveform selection and test parameter setting; the lower section is for waveform playback display and setting. This mode can detect the dynamic light intensity function of the DUT, so the PPG-2TF-660 2.0 can send corresponding signals as the same intensity to the DUT according to the change in light intensity.

Upper section:

Figure 69: Auto Test SpO₂ Interface


- (1) **BPM:** Adjust for different heart rates. The value is from 10 BPM to 300 BPM.
- (2) **SpO₂:** Adjust for different heart rates. The value is from 1% to 100%.
- (3) **IR-PI Setting:** Set the PI value of Infrared. The value is from 0.01% to 20%.
- (4) **Transmission Rate:** The user can choose to simulate 6 different transmission rates (Light & Thin Finger, Light & Medium Finger, Normal Medium Finger, Dark Medium Finger, Dark & Thick Finger and Neonatal Foot).
- (5) **Signal Strength:** Detect the signal strength of the DUT to set up a proper measuring position for test.
- (6) **Table:** The dropdown list provides 4 reference SpO₂ tables (Masimo, Nellcor, GE, and Philips) for users to compare. To create the DUT's SpO₂ table for verification, please click the "Table" and refer to the instructions below.

If users already have self-defined SpO₂ tables with the same names as the reference SpO₂ tables (G_R-curve_V2, M_R-curve_V2, N_R-curve_V2, and P_R-curve_V2), the dropdown list would not show the Masimo, Nellcor, GE, and Philips reference SpO₂ tables.

To load the 4 reference SpO₂ tables, first, please go to the user's SpO₂ folder "C:\Users\admin\AppData\Local\WhaleTeq\AECG\SpO2" and move the original file of the user-defined SpO₂ table to the desktop, then rename it.

Second, delete the entire user's SpO₂ folder and restart the AECG100 software, so the system will automatically create a new user's SpO₂ folder with imported Masimo, Nellcor, GE, and Philips reference SpO₂ tables.

Finally, move the renamed user-defined SpO₂ table into the new user's SpO₂ folder, then users can return to the dropdown list to select from the 4 reference SpO₂ tables and the user-defined SpO₂ table.

Note: The Masimo, Nellcor, GE, and Philips reference SpO₂ tables are not provided by their respective owners. The data are collected through the AECG100 main console measurement and for reference only.

**The UI is illustration only. For detailed display please check on your software UI.*


Set up the SpO₂ parameter and transmission rate, then click "Play" at the lower section of the Auto Test SpO₂ tab to send signals to the DUT as figure 70 shows.

Note: If the DUT can't measure the SpO₂ value or its SpO₂ measured value fluctuates greatly, please adjust the measuring position or select another transmission rate to test.

If the optical signals emitted by the DUT is in the critical range of PD recognition of the PPG-2TF-660 2.0, it may affect the stability of the LED output signals of the PPG-2TF-660 2.0, and lead to the DUT continuously calculating the SpO₂ value and failing to display it.


If further assistance is needed, please contact WhaleTeq.

Figure 70: Auto Test SpO₂ mode is operating




Click “Stop” () to show the DUT’s DC values of R and IR, as the figure 71.

Figure 71: The DUT’s DC values of R and IR appear



Click “Table” to bring up the SpO₂ Table window, then click “New Table” and create a name for a new table. The DC value of R and AC and DC values of IR are automatically filled in, as the figure 72.


Figure 72: The DC value of R and AC and DC values of IR are automatically filled in



R - AC (mV)	R - DC (mV)	IR - AC (mV)	IR - DC (mV)	SpO2
305	9.38	375	375	

Fill in a designated AC value of R, then the DUT shows the SpO₂ value. Fill in the SpO₂ value in the table and click “Save” as the figure 73.


Figure 73: Fill in the AC value of R and the SpO₂ value and save



R - AC (mV)	R - DC (mV)	IR - AC (mV)	IR - DC (mV)	SpO2
4.5	305	9.38	375	96
	305	9.38	375	

Repeat the above steps to gather enough information, then click “Graph” to bring up the DUT’s R curve.

Figure 74: The DUT’s R curve




Lower Section:

* The UI is illustration only. For detailed display please check on oscilloscope.


Signal Tab:

Figure 75: Signal Tab




Sampling Tab: Sampling PD

Figure 76: Sampling PD



Sampling Tab: Sampling LED Switch

Figure 77: Sampling LED Switch



- (1) **Signal tab:** Users can play waveform with preset parameters.
- (2) **Sampling tab for PD/LED Switch:** Users can observe the DUT LED brightness and AECG100 LED switch status.
- (3) **Play/Stop:** Play the selected waveform with preset parameters. Once stopped, play from the beginning.
- (4) **Waveform Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec.
- (5) **Inverted/Sync Pulse/Ambient Light:**

Table 2: Inverted/Sync Pulse/Ambient Light Function Description

Inverted: On	AECG100 outputs PPG waveform upside down.
Inverted: Off	AECG100 output PPG waveform as per the window display.
Sync Pulse: On	LED behaviors of AECG100 synchronize with DUT LED.
Sync Pulse: Off	AECG100 LED remains on.
Ambient Light: On	The selected ambient light is activated and shown here. Please refer to figure 21 to see the 14 options of ambient light signals.

Ambient Light: Off	The ambient light function is turned off.
--------------------	---

(6) **Sampling:** Use PD of AECG100 to measure intensities of DUT LED.

(7) **Signal:**

PD-RED/ PD-Infrared:

It shows the intensity and behaviors of DUT LED sampled by AECG100's PD. Displayed in **Blue** and **Purple** curves.

Switch-RED/ Switch-Infrared:

It shows the timing AECG100 switches LED on or off. Waveform displays low means AECG100 turn on LED. Waveform displays high means AECG100 turns off LED. Displayed in **Blue** and **Red** curves.

PD/ Switch selection is memorized.

(8) **Freeze:** After enabling this function, the display of PD/ LED switch sampling would stay as it is.

(9) **Max Peak:** Display the peak value of DUT LED, sampled by AECG100 PD.

(10) **Time Axis:** Adjust the time axis of PD sampling and switch.


(11) **Enlarge:** Click to better view the sampling details.

4.6 SpO₂ Mode

It requires connecting the PPG-2R-940, PPG-2R-880 or PPG-2TF-660 2.0 module to initiate SpO₂ test mode. SpO₂ test mode can be separated into 2 sections. The upper section is for waveform selection and test parameter setting; the lower section is for waveform playback display and setting.

Upper section:

Figure 78: SpO₂ mode UI for reflectance SpO₂ module and transmittance SpO₂ module




- (1) **BPM:** Adjust for different heart rates. The value is from 10 BPM to 300 BPM.
- (2) **R Value:** The R Value is the ratio of RED LED PI percentage and Infrared LED PI percentage. Selecting PI (R) means changing the SpO₂ value by altering the PI of the red LED; selecting PI (IR) means changing the SpO₂ value by altering the PI of the infrared LED.
- (3) **R curve, the SpO₂ Level Equation Adjustment:** Default equation is the Webster linear empirical calibration formula: $\text{SpO}_2 \text{ level (\%)} = 110.0 - 25.0 \times R$, where R is the R value from (2).

For known R curve, users simply adjust the SpO₂ value (by indirectly changing the RED or Infrared parameters) to ensure the DUT SpO₂ value changes along with that of AECG's. Key-in the desired SpO₂ level (%) without modifying the intercept and slope, the R value will be generated in accordance with R-Curve equation. The same R Value is used to display the corresponding RED/Infrared parameters.

For unknown R curve, users may obtain the intercept and slope of the R-Curve equation by using the SpO₂ Table (Please refer to the description of (1) Table).

Figure 79: Setting R Curve



Waveform: PPG ☐ Use SpO2 Table R Curve

SpO2: 98 % = Intercept 110.0 + Slope -25.0 × R Degree: 1

R Value: 0.500 = ☒ PI (R) / ☐ PI (IR) RED/Infrared LED Parameter Setting

RED

☐ Lock AC ☒ Lock DC

PI: 2.000 % = AC: 12.50 mV / DC: 625 mV

Output DC = 625 + 0 mV

Infrared


☐ Lock AC ☒ Lock DC

PI: 4.000 % = AC: 25.00 mV / DC: 625 mV

Output DC = 625 + 0 mV

- (4) **Output Waveform Selection:** Select to output different waveform types (ex. Sine, Triangle, or PPG).
- (5) **Use SpO₂ Table:**
Option 1. User can click “Table” to build SpO₂ table with specified parameters of R/IR LED.

Figure 80: Using SpO₂ Table




Waveform: PPG ☒ Use SpO2 Table Table: 12

SpO2: 98 %

R Value: 0.500 = ☒ PI (R) / ☐ PI (IR)

After completing the SpO₂ table, click “Graph” to obtain the R curve equation.

Figure 81: Equation for Obtaining the R Curve



Click  at the upper-right corner to copy the R curve to the main screen. Users can directly set designated SpO₂ level (%), and AECG100 will output optical signals accordingly. Please notice that the SpO₂ level can only be set in accordance with the SpO₂ values stored in (1) Table. AECG100 automatically outputs optical signals.

Option 2. Select already-created table from the drop-down menu, the function “Use Calibration Curve” appears.


Figure 82: Use Calibration Curve Function



The interface shows a 'Waveform' dropdown set to 'PPG'. There is a checked checkbox for 'Use SpO2 Table' and a 'Table' dropdown set to 'table1'. The 'SpO2' input is set to '83 %'. The 'R Value' input is set to '1.000'. Below these, there is an equals sign followed by two radio buttons: 'PI (R)' (which is selected) and 'PI (IR)'.

When checking “Use Calibration Curve” and select “Degree” (of Polynomial), a R-Curve equation is generated based on the data points entered in the table. Any SpO₂ level (in integer) can be set with displayed equation.

Figure 83: Use Calibration Curve Interface



The interface shows the 'Waveform' dropdown set to 'PPG'. The 'Use SpO2 Table' checkbox is checked, and the 'Table' dropdown is set to 'Sample'. The 'Use Calibration Curve' checkbox is also checked. The 'SpO2' input is set to '86 %'. To the right of this, an equation is displayed: $111.1 + -22.6 \times R$. Further right, the 'Degree' is set to '1'. The 'R Value' input is set to '1.111'. Below these, there is an equals sign followed by two radio buttons: 'PI (R)' (which is selected) and 'PI (IR)'.

After adjusting parameters of RED or Infrared LED, R value and SpO₂ level are changed simultaneously. Press “Play” to have AECG100 output optical signals.


- (6) **Degree:** Change the degree of polynomial between linear and quadratic when not using the SpO₂ table.
- (7) **PI value:** PI refers to the Perfusion Index (PI). Fix AC value to adjust DC and PI values, or fix DC value to adjust AC and PI values.
- (8) **Output DC (Fine-Tune):** As ambient light and inner electrical circuit offset of DUT would affect the DC value received by DUT, users can fine-tune the Output DC to minimize the influence. The default value is 0.

Note: Due to the following reasons, the PI measured value may not match the setting value: the existence of dark current in the LED making it require a certain driving current to light, the luminous power of the LED, and the difference in calculations from the PI formula. When the PI measured value doesn’t match the setting value, please adjust the Output DC compensation value to calibrate the PI measured value.

The AECG100 provides two options: "AC above DC" and "AC below DC". For details, please refer to "[4.1.1 PPG Configuration](#)". The following description and illustration use "AC above DC" as an example.

The PI formula of WhaleTeq is " $PI = AC/DC$ ", and the figure below shows the AC and DC ratio.

Figure 84: AC and DC Ratio



Note:

- a. Adjusting the DC compensation value will indirectly affect the SpO_2 value.
- b. When using the R curve from Table, changing the DC compensation value will also affect the SpO_2 value of the R curve.

To adjust the DC compensation value, for example:

Set $PI=3$, $AC=15$, $DC=500$, compensation value=10.

If the PI measured value is 4, which is higher than the setting value, the compensation value should be increased to 15 to lower the measured value near 3.

If the PI measured value is 2, which is lower than the setting value, the compensation value should be decreased to 5 to raise the measured value near 3.


Adjust the compensation value until the PI measured value is the same as the setting value. According to the actual situation, the compensation value can be adjusted to a negative number.

If further assistance is needed, please contact WhaleTeq.

- (9) **AC value:** To simulate the artery volume change of artery diastolic phase and systolic phases.
- (10) **DC value:** To simulate reflected optical signal of the average artery and vein volume change from skin tissue, bone, and muscle.
- (11) **Parameter Lock and Adjustment:** Lock AC value to adjust PI and DC value or lock DC value to adjust PI and AC value.
- (12) **Table** (Upon clicking "Use SpO_2 Table"): An SpO_2 level matching table is built by entering AC and DC values of RED and Infrared LEDs, along with the SpO_2 values


resulted from DUT. These parameters are used to adjust the intercept and slope of the linear (Degree 1) or quadratic (Degree 2) equations.

Figure 85: Using SpO₂ Table



Click “New Table” button to add a SpO₂ table, and DUT shall be put onto AECG100 to test. As shown in the following figure 86, users may set PPG R-AC (12.5), R-DC (625), IR-AC (25), and IR-DC (625). AECG100 automatically output optical signal. Users shall observe the SpO₂ value from DUT, and fill this SpO₂ value into the table.


Figure 86: Build SpO₂ Table (1)



R - AC (mV)	R - DC (mV)	IR - AC (mV)	IR - DC (mV)	SpO2
12.5	625	25	625	

As shown in the following figure 87, user can change the AC values of R or IR (one at a time) to conduct a series of tests to get SpO₂ values and fill them into the SpO₂ table. Press “Save” button to save the table as a file.


Figure 87: Build SpO₂ Table (2)



R - AC (mV)	R - DC (mV)	IR - AC (mV)	IR - DC (mV)	SpO2
12.5	625	25	625	98
15	625	25	625	95
17.5	625	25	625	93

After completing the SpO₂ table, press “Graph” button to obtain a R-curve based on the SpO₂ table, and users may adjust the degree of polynomial. When selecting simple equation, AECG100 software will determine the equation with intercept and slope. Press upload  at the upper-right corner to adjust the R-Curve equation for DUT.

Figure 88: Automatic Calculation of the Intercept and Slope of the SpO₂




Lower Section:

* The UI is illustration only. For detailed display please check on oscilloscope.


Signal Tab

Figure 89: Signal Tab




Sampling Tab: Sampling PD

Figure 90: Sampling PD




Sampling Tab: Sampling LED Switch

Figure 91: Sampling LED Switch




Player Tab

Figure 92: Player Tab



- (1) **Signal tab:** Users can reset/save/recall/play waveform with preset parameters.
- (2) **Sampling tab for PD/ LED Switch:** Users can observe the DUT LED brightness and AECG100 LED switch status.
- (3) **Player tab:** Users can load/ play/ loop raw data file.
- (4) **Reset:** Resume the default setting in the upper section.
- (5) **Save:** Save the preset test parameters from the upper section into Standalone (device Mode A/B/C), PC file (in *.spo), or Waveform Raw (in *.txt) format.


Figure 93: Save Setting



Note: Standalone (device Mode A/B/C) and PC file can be used in (1) Signal tab “Recall” and Auto Sequence Mode. Only Waveform Raw can be played in (2) Player tab.

Saving in Waveform Raw requires license purchase. Please send the “AECG ID” to WhaleTeq to purchase and obtain the “Activation Key” to access the software.


Figure 94: Enter Activation Key Screen Display



- (6) **Recall:** Load the previously saved test parameters stored in Standalone (device Mode A/B/C) or as a PC file (*.spo format).
- (7) **Play/Apply:** Play the selected waveform with preset parameters. After clicking “Play”, the button changes to “Apply”. Parameters can be adjusted during waveform playback. Click “Apply” to output the waveform using the new settings.

To stop playback, click the Stop button () next to the PPG tab.

Figure 95: "Play/Apply" Button and "Stop" Button



- (8) **Waveform Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec.
- (9) **Inverted/Sync Pulse:**

Table 3: Inverted/ Sync Pulse Function Description

Inverted: On	AECG100 outputs PPG waveform upside down.
Inverted: Off	AECG100 output PPG waveform as per the window display.
Sync Pulse: On	LED behaviors of AECG100 synchronize with DUT LED.
Sync Pulse: Off	AECG100 LED remains on.

- (10) **Sampling:** Use PD of AECG100 to measure intensities of DUT LED.
- (11) **Signal:**

PD-RED/ PD-Infrared:

It shows the intensity and behaviors of DUT LED sampled by AECG100's PD. Displayed in **Blue** and **Purple** curves.

Switch-RED/ Switch-Infrared:

It shows the timing AECG100 switches LED on or off. Waveform displays low means AECG100 turn on LED. Waveform displays high means AECG100 turns off LED. Displayed in **Blue** and **Red** curves.


PD/ Switch selection is memorized.

- (12) **Freeze:** After enabling this function, the display of PD/ LED switch sampling would stay

as it is.

- (13) **Max Peak:** Display the peak value of DUT LED, sampled by AECG100 PD.
- (14) **Time Axis:** Adjust the time axis of PD sampling and switch.
- (15) **Enlarge:** Click to better view the sampling details.
- (16) **Load:** To load PPG raw data for each channel (PPG RED/ PPG Infrared). Select channel first, and then load PPG RED or PPG Infrared raw data in the “File” section accordingly. Raw data file is either saved from (1) Signal tab “Waveform Raw” or self-constructed according to WhaleTeq rule (click “Help” for more details). “Total Length” indicates the total waveform playback time. User has to manually adjust “Output Setting” to assure AECG100 output signal with suitable parameters.

Figure 96: Waveform Player




- (17) **Play/Stop:** Play the selected raw data file in *.txt format. Once stopped, play from the beginning.
- (18) **Loop:** Play the loaded waveform repeatedly.
- (19) **Current Position:** Display the timing of the played raw data.
- (20) **Display Scale:** Adjust the display scale for 2 sec, 5 sec, or 10 sec time frames of AECG100 PD sampling windows.
- (21) **Output waveform selection:** Select to play R and IR signals together or separately.

4.7 Auto Sequence Mode


Auto Sequence mode allows users to use the saved waveform file from ECG/PWTT/SpO₂/PPG tabs to edit the sequence and testing time as an auto-test file. This auto-test file can be programmed to repeat.

Figure 97: Auto Sequence Mode



- (1) **Add:** To add new waveform file of ECG/SpO₂/PWTT/PPG to auto sequence combination. Files must be saved from Standalone option or as PC file.

Figure 98: Add Waveform Files



- (2) **Save:** To save auto sequence combination as an automatic testing sequence (in *.seq format).
- (3) **Recall:** To load the saved auto sequence.
- (4) **Reset:** To remove all the loaded waveform files.
- (5) **Testing Combination:** Test combinations displayed in an assigned sequence.
- (6) **Sequence Cursor:** Drag the file to change the order of the sequence played.
- (7) **Waveform Parameter Display:** To display the test parameters of selected test sequences. **Unable** to modify the test parameters.
- (8) **Play/ Stop:** Play the selected test sequence. Once stopped, play from the beginning.
- (9) **Loop:** To replay the selected test sequence repeatedly.
- (10) **Total:** Show the total playback time of the set sequence.

4.8 Supported Raw Data File Format

AECG100 support Text file (*.txt) only and file content describes as below:

File Format:

[sampling frequency]
[number of samples per signal]
[number of signals]
[signal description (signal-1)],[signal description (signal-2)], ...
[sample data-1 (signal-1)],[sample data-1 (signal-2)], ...
[sample data-2 (signal-1)],[sample data-2 (signal-2)], ...
...
[sample data-N (signal-1)],[sample data-N (signal-2)], ...

Description:

sample frequency

Input the frequency of sample data

number of samples per signal

The limitation is related to the available memory size of PC system. If PC system has available memory for 1Gb, the maximum number of single channel sample data would be 131,072.

number of signals

This number must be greater than 1.

signal description

The description text for the signal.

sample data

The raw data unit is mV.

For ECG, the data range is [-5, 5] mV.

For PPG, there are no limits for the range of the raw data, but you can scale the range to [0, AC], which can be adjusted in AECG100 PC software. If we set AC level for 10mV in AECG100 PC software, this means the [0, AC] becomes [0,10]. Then AECG100 PC software will automatically calculate the sample data value to a specific AC value by the following formula:

$$[\text{Data Value} / (\text{Maximum Data Value} - \text{Minimum Data Value})] * \text{Maximum AC Level}$$

For example, if we setup AC level = 10mV while the maximum data value is 12.500 and the minimum data value is 0.000, the sample data 0.021 will become $[0.021 / (12.500 - 0.000)] * 10 = 0.0168$ mV.

Example:

1000

1000

2

sine wave-5,sine wave-10

0.000,0.000

0.031,0.063

0.063,0.126

0.094,0.188

0.126,0.251

0.157,0.314

0.188,0.377

0.220,0.440

0.251,0.502

0.283,0.565

0.314,0.628

0.345,0.691

0.377,0.753

0.408,0.816

0.439,0.879

0.471,0.941

0.502,1.004

0.533,1.066

0.564,1.129

0.595,1.191

0.627,1.253

0.658,1.316

0.689,1.378

0.720,1.440

0.751,1.502

0.782,1.564

0.813,1.626

0.844,1.688

.....

-1.029,-2.059

-0.999,-1.997

-0.968,-1.935

-0.937,-1.874

-0.906,-1.812

-0.875,-1.750


-0.844,-1.688

-0.813,-1.626

-0.782,-1.564

-0.751,-1.502

-0.720,-1.440



-0.689,-1.378
 -0.658,-1.316
 -0.627,-1.253
 -0.595,-1.191
 -0.564,-1.129
 -0.533,-1.066
 -0.502,-1.004
 -0.471,-0.941
 -0.439,-0.879
 -0.408,-0.816
 -0.377,-0.753
 -0.345,-0.691
 -0.314,-0.628
 -0.283,-0.565
 -0.251,-0.502
 -0.220,-0.440
 -0.188,-0.377
 -0.157,-0.314
 -0.126,-0.251
 -0.094,-0.188
 -0.063,-0.126
 -0.031,-0.063

5 Software Development Kit (SDK)

WhaleTEQ provides the software development kit (SDK) for AECG100. All test parameters correspond to specific SDK commands and DLL (Dynamic-link library) shared library can be used for efficient program binding and version upgrade. Support C/C++ header, C# interface, third-party tools, and script language integration.

6 Calibration and Validation

WhaleTEQ original calibration service is equipped with calibration equipment specially designed for physiological simulator to ensure the accuracy of calibration, and can calibrate the offset value of the device within the original specification of WhaleTEQ. Under normal use, the device is recommended to be calibrated once a year.

There are three kinds of calibration/validation methods for AECG100: calibrated by Masimo Radical-7 Pulse CO-Oximeter, calibrated by "Covidien" Nellcor Portable SpO₂ Patient Monitoring System, or measuring electrical and LED/PD parameters including output voltage, frequency, LED intensity, and PD ability to detect light. Any of the above methods require traceable equipment. Steps for Calibration/Validation methods are also available upon request. Please contact WhaleTEQ for more information (see section 0).


Note: If WhaleTeq detects that the components of the device are damaged and makes it impossible to adjust, it shall be sent back for maintenance.

6.1 Self-calibration

Self-calibration assists the user calibrates the AECG100 to quickly confirm the signal quality before testing, not to replace the original calibration service recommended every year. Please follow the steps below to conduct self-calibration.

1. Set up the parameters of the AECG100 AP to “Square, 5mV, 0.1 Hz” and output to the RA lead electrode as the figure shown below:

Figure 99: AECG100 Interface Setup



2. Connect the multimeter to RA and LA of the AECG100, and measure the DC mV. The value should be in 1% of 5mV because the output amplitude of the AECG100 gives alternating 5s (0.1 Hz square wave) phases at -2.5mV and +2.5mV, which the multimeter is zeroed (delta function) at one phase (e.g., -2.5mV), with reading taken from the other phase (e.g., +2.5mV) to obtain the 5mV peak-peak value.


Note: Please use the multimeter which is 6 1/2 (6 1/2 digits) or more.

Figure 100: Self-Calibration Setup




3. The AECG100 $\pm 300\text{mV}$ DC offset check is shown as the red square in the figure below. The AECG100 connects DC in series with electrode wire (in the case, RA).

Figure 101: AECG100 $\pm 300\text{mV}$ DC offset



4. The user can verify the DC voltage by setting up the parameters of the AECG100 AP to “Square, 0mV, 0.1Hz and DC Offset Setting to 300mV”.

Figure 102: DC Voltage Verification (300mV)



5. Connect the multimeter to RA and LA of the AECG100 and measure the DC voltage. The value should be in 1% of 300mV. The setup is shown in the below figure.


Note: The AECG100 uses a supercapacitor to maintain a 300mV DC voltage. This allows a precise and stable 300mV DC offset to be added to the primary waveform for at least 3 minutes without affecting the quality of the primary waveform (for continuous use, it is recommended to limit the duration to no more than 10 minutes). When the 300mV DC voltage is not in use (the setting is set to zero), the AECG100 automatically charges the supercapacitor.

Figure 103: Self-Calibration Setup



6. If the user wants to check the DC voltage other than 300mV, set the DC voltage from -1000mV to +1000mV with 5% accuracy. Please look at the figure below for details.
Note: This extra DC voltage can support some other than 300mV testing.

Figure 104: DC Voltage Verification (>300mV)



7 Troubleshooting

- (1) If the PPG module is accidentally separated from AECG100 main console unit in operation, please follow the below steps to have the test system work properly.

Step1: Turn off the power switch on AECG100 main console unit and assure the power indicator is off.

Step2: Re-connect the PPG module to the AECG100 main console.

Step3: Turn on the power switch on AECG100 main console unit and assure the power indicator is on.

- (2) When Red LED of the power indicator remains on:

If Red LED remains on, the AECG100 system is crashed. Please try turning off and then turning on the AECG100 test system.

- (3) No LED display at the power indicator:
For no LED display, either the system is crashed or no power is supplied to the test system. Please try to unplug and re-plug in the USB cable, or try turning off and then turning on the AECG100 test system.

8 Cautions

- (1) Mode A/B/C is saved in AECG100 main console, while info stored within Mode A/B/C may correspond to different variable values for different PPG modules connected. Therefore, when testing AECG100 main console with different PPG modules, re-saving Mode A/B/C is required to obtain desired test results.
- (2) When a stable and firm connection between AECG100 main console and PPG modules is desired (e.g., moving the entire system around), it is recommended to fasten with a DB15 cable in between. The cable spec is DB15 male to female.
- (3) It is suggested to warm up AECG100 Test System for at least 30 minutes before testing.
- (4) Before using PPG-related functions, please assure the distance between the PPG module head and DUT PPG sensor is fixed.
- (5) During testing, it is essential to minimize the ambient light, as it would influence the test result as well.
- (6) LED luminous decay occurs as time goes on. It is recommended to send the AECG100 units to WhaleTeq for calibration every year to replace the LED base if needed (depends on usage frequency) to ensure LED brightness is qualified. Please contact WhaleTeq Co, Ltd for more details.
- (7) When upgrading AECG100 firmware, DO NOT disconnect the USB cable or close the software during the process.
- (8) Warranty voids if QC PASS label is removed or tampered with.
- (9) This is a professional testing instrument instead of a medical device. It is for testing only and will not be used on human or clinical use.

9 Specification

9.1 ECG Test Mode

Table 4: ECG Test Mode Specification

Parameters		Specifications
Main Output Voltage	Resolution	2.5 μ V (DAC resolution)
	Accuracy	$\pm 1\%$ for amplitudes of 0.5mVpp or higher
Frequency/Pulse Repetition Rate	Accuracy	$\pm 1\%$
Pulse Duration/Timing	Accuracy	± 1 ms
Pacing Pulse Amplitude	Setting Range	-1000mV — +1000mV
	Accuracy	± 2 mV pulse: $\pm 1\%$ >2mV or <-2mV pulse: $\pm 10\%$
Pacing Pulse Width	Setting Range	0.1ms — 2ms
	Minimum Step Size	0.1ms
	Accuracy	$\pm 10\%$
Pacing Pulse Characteristics	Rise / fall time	≤ 100 ms
	Overshoot	<1%
	Settling time	<1%
Sample Rate	Rate	50 — 40kHz (Normal mode/ Standalone mode); 40kHz (Raw data mode)
	Accuracy	Depend on system clock accuracy
DC Offset (fixed, noise free, sourced from internal super capacitor)	Range	-300mV, +300mV
	Accuracy	$\pm 1\%$
DC Offset (variable, may include up to 50 μ Vpp noise)	Setting Range	-500mV — +500mV
	Accuracy	$\pm 1\%$
RCA Output Amplitude	Range	ECG electrode output x1000, max 10V
	Accuracy	$\pm 1\%$ for amplitudes of 0.5Vpp or higher
S/N Ratio		>51dB (with USB isolator)

9.2 ECG Test Mode Parameters

Table 5: ECG Test Mode Parameters

Parameters		Setting Range	Default Values	Minimum Step Size
Output Waveform		ECG/Sine/Triangle/Square/Exponential/Rectangle pulse/Triangle pulse	ECG	-
Output Voltage (ECG)	Amplitude (p-p)	-5.71 — 5.71mV	1mv	0.1mv
	R Wave	-5 — 5mV	0.88mV	0.05mV
	T Wave	0 — 5mV	0.2mV	0.05mV
	P Wave	0 — 1mV	0.2mV	0.05mV
	ST Deviation	-1 — 1mV	0mV	0.05mV
Output Time (ECG)	PR Interval	100 — 200ms	160ms	1ms
	QT Interval	100 — 840ms	100ms	1ms
	QRS Duration	10 — 200ms	350ms	1ms
	Heart Rate	10 — 300BPM	60BPM	1BPM
Output Voltage (Sine/Triangle/Square)	Amplitude	-10 — 10mV	1mV	0.01mV
Output Voltage (Exponential/Rectangle pulse/Triangle pulse)	Amplitude	-5 — 5mV	1mV	0.01mV
Output Time (Sine/Triangle/Square/Exponential/Rectangle pulse/Triangle pulse)	Pulse Width	0 — 20000ms (Triangle pulse/Rectangle pulse)	100ms	10ms
	Frequency	0.05 — 500Hz (Sine/Triangle/Square) 0.17 — 5Hz (Exponential) 0.05 — 5Hz (Rectangle pulse/Triangle pulse)	1Hz	0.01Hz
Output Lead Electrode	Electrode	RA/R, LA/L	RA/R	-
DC offset	Offset	-300mV/+300mV	0mV	300mV
	Offset (Variable)	-500 — +500mV	0mV	5mV
	Variable	Select/Unselect	Unselect	-
Input Impedance Test	620kΩ/4.7nF	On/Off	On	-
Noise Generator	Amplitude	0 — 2mV (limited by R wave max)	0.1mV	0.05mV
	Frequency	Off/50/60/100/120Hz	Off	-
Pacemaker	Pacing Amplitude	-1000 — 1000mV	2mV	2mV
	Pacing Duration	1 — 2ms	2ms	0.1ms

Parameters		Setting Range	Default Values	Minimum Step Size
	Sync with main function	Enable/Disable	Enable	-
	Pacing Rate	30 — 300BPM	60BPM	10BPM
Respiration	Rate	4 — 200BrPM	20BrPM	1BrPM
	Basic Level	1000/1500/2000Ω	1000Ω	-
	Variations	1 — 5Ω	1Ω	0.5Ω
	Ratio	1 — 5	1	1
	Apnea Duration	0 — 60s	Disable/10s	1s
	Apnea cycle	1 — 10min	1min	1min
Frequency Scan	Amplitude	-10mV — +10mV	1mV	0.1mV
	Start	0.67 — 500Hz	0.67Hz	0.1Hz
	Stop	0.05 — 500Hz	150Hz	0.1Hz
	Duration	10 — 180s	30s	10s
Auto Heart Rate	Heart Rate	30/60/120/180/200BPM	30/60/120/180 BPM	-
	QRS Amplitude	0.5/1/2/5mV	0.5/1/2/5mV	-
	QRS Duration	40/70/80/100/120ms	70/100/120ms	-
	Intervals	5 — 60s	30s	5s
Signal play	Time Scale	5/10/20 mm/mV	10mm/mV	-
Raw data play	Loop	Enable/Disable	Enable	-
	Time Scale	5/10/20 mm/mV	10mm/mV	-
RLD (RL/N1, RL/N2) Input	Test Voltage	1.5V	-	-

9.3 PPG Test Mode (with Reflectance PPG Module)

Table 6: PPG Test Mode Specification (with Reflectance PPG Module)

Parameters		Specifications
Heart Rate	Setting Range	10 — 300BPM
	Minimum Step Size	1BPM
	Accuracy	±1BPM
LED DC Level Reference Output	Setting Range	100 — 3000mV
	Minimum Step Size	1mV
	Setting Range	0.75 — 30mV

Parameters		Specifications
LED AC Level Reference Output	Minimum Step Size	0.01mV
Lumen [§]	Setting Range	50 – 925 Lux (full range) (5mm from diffusion film)
	Resolution	(1/3000) full range
	Accuracy	±6%
Light Wavelength	Range	525 / 660 / 880 / 940nm
	Accuracy	±10nm
LED Scan Rate	Rate	50 – 40kHz (Normal mode/ Standalone mode); 10kHz (Raw data mode)
	Accuracy	±5μs
PD Sample Rate	Rate	250kHz (single channel)
	Accuracy	±5μs
PD Response Time	Rising	1μs Typical*
	Falling	1μs Typical*

[§] The data is for PPG-1R-525 module.

* The PD response time will vary with the light intensity of the DUT.

9.4 PPG Test Mode Parameters (with Reflectance PPG Module)

Table 7: PPG Test Mode Parameters (with Reflectance PPG Module)

Parameters	Setting Range	Default Values	Minimum Step Size
Output Waveform	Sine / Triangle / Square / PPG	PPG	-
BPM	10 – 300BPM	60BPM	1BPM
Frequency	0.17 – 5	1.00	0.01
Green / Red / Infrared (Voltage)			
PI	0.025 – 30.000%	2.000%	-
DC	100 – 3000mV	625mV	1mV
Systolic Peak (SP) (AC)	0.75 – 30.00mV	12.50mV	0.01mV
Dicrotic Notch (DN)	0.75 – 30.00mV	7.00mV	0.01mV
Diastolic Peak (DP)	0.75 – 30.00mV	8.00mV	0.01mV
Lock	Lock DC: Only DC of Voltage locked	Lock DC	-

Parameters		Setting Range	Default Values	Minimum Step Size
		Lock AC: AC, DN, DP of Voltage locked		
Red / Infrared (Time)				
Systolic Peak (SP) (AC)		0 – 1000ms (60BPM)	150ms	1ms
Dicrotic Notch (DN)		0 – 1000ms (60BPM)	360ms	1ms
Diastolic Peak (DP)		0 – 1000ms (60BPM)	460ms	1ms
Noise Generator (Time)				
Frequency		off / 0.5 / 1 / 2 / 3 / 5 / 10 / 25 / 50 / 60 / 100 / 120 / 1K / 5K Hz / White Noise	off	-
Amplitude		0.05 – 2.00mV	0mV	0.05mV
Respiration				
Respiration Rate		1 – 150BrPM	20BrPM	1BrPM
Inhale-Exhale Ratio		1:1, 1:2, 1:3, 1:4, 1:5	1:1	1
Wave Modulation		Baseline / Amplitude / Frequency	Baseline / Amplitude / Frequency	-
Respiration – Baseline Modulation		Variation – R: 1 – 16% Variation – IR: 1 – 16%	1% 1%	1% 1%
Respiration – Amplitude Modulation				
Respiration – Frequency Modulation				
Apnea Selection	Duration	1 – 60s	10s	1s
	Cycle	1 – 10min	1min	1min

9.5 PWTT Test Mode (with Reflectance and Transmittance PPG Module)

Table 8: PWTT Test Mode Specification (with Reflectance and Transmittance PPG Module)

Parameters		Specifications
Time Difference (PTTp, PTTf)	Setting Range	0 – 5999ms (for the heart rate setting as 10BPM. As the heart rate value increases, the setting range of time difference will decrease accordingly.)
	Minimum Step Size	1ms
	Accuracy	±1ms

9.6 SpO₂ Test Mode (with Reflectance PPG Module)

Table 9: SpO₂ Test Mode Specification (with Reflectance PPG Module)

Parameters		Specifications
Heart Rate	Setting Range	10 – 300BPM
	Minimum Step Size	1BPM
	Accuracy	±1BPM
LED DC Level Reference Output	Setting Range	100 – 3000mV
	Minimum Step Size	1mV
LED AC Level Reference Output	Setting Range	0.75 – 30mV
	Minimum Step Size	0.01mV
PI (AC level/DC level)	Setting Range	0.025% – 30% (AC/DC, varies with AC or DC level)
LED Light Wavelength	Range	Red: 660nm; Infrared: 940nm/880nm
	Accuracy	Red: ±10nm; Infrared: ±10nm
Red Light Absolute Irradiance (100%) [§]	Intensity	3.55 mW/m ²
	Accuracy	±15%
Infrared Light Absolute Irradiance (100%) [§]	Intensity	6.65 mW/m ²
	Accuracy	±15%
LED Scan Rate	Rate	50 – 40kHz (Normal mode/ Standalone mode); 10kHz (Raw data mode)
	Accuracy	±5μs
PD Sample Rate	Rate	250kHz (single channel)
	Accuracy	±5μs
PD Response Time	Rising	1μs Typical*
	Falling	1μs Typical*
SpO ₂ (%)	Setting Range	1 – 100 (%)
	Minimum Step Size	1 (%)

Parameters		Specifications
	Accuracy	$\pm 1\%$ + specified accuracy of the DUT (using Masimo Radical-7 Pulse CO-Oximeter or “Covidien” Nellcor Portable SpO ₂ Patient Monitoring System)

[§] Data Collection Method: To connect the spectrometer with a 2-inch integrating sphere, and fix the integrating sphere on the DUT to measure the absolute irradiance of the LED of the DUT.

* PD response time varies with the light intensity of the DUT.

9.7 SpO₂ Test Mode Parameters (with Reflectance PPG Module)

Table 10: SpO₂ Test Mode Parameters (with Reflectance PPG Module)

Parameters	Setting Range	Default Values	Minimum Step Size
Output Waveform	Sine / Triangle / PPG	PPG	-
BPM	10 — 300BPM	60BPM	1BPM
SpO ₂	0 — 100%	98%	1%
Red			
PI (AC level/DC level)	0.025 — 30%	2.000%	0.001%
AC	0.75 — 30mV	12.50mV	0.01mV
DC	100 — 3000mV	625mV	1mV
Output DC (offset)*	0 — 2000mV	0mV	1mV
Lock	Lock AC/DC	Lock DC	-
Infrared			
PI (AC level/DC level)	0.025 — 30%	4.000%	0.001%
AC	0.75 — 30mV	25.00mV	0.01mV
DC	100 — 3000mV	625mV	1mV
Output DC (offset)*	0 — 2000mV	0mV	1mV
Lock	Lock AC/DC	Lock DC	-

*Note: The sum of the Output DC (offset) value and the DC value has an upper limit of 3000mV. For example, if the DC value is already set to 3000mV, the Output DC (offset) value cannot be increased further.

9.8 PPG Test Mode Parameters (with Transmittance PPG Module)

Table 11: PPG Test Mode Parameters (with Transmittance PPG Module)

Parameters		Setting Range	Default Values	Minimum Step Size
Output Waveform		Sine / Triangle / Square / PPG	PPG	-
BPM		10 — 300BPM	60BPM	1BPM
Frequency		0.17 — 5	1.00	0.01
Red / Infrared (Voltage)				
PI		0.01 — 20.000%	2.000%	-
DC		300 — 3000mV	625mV	1mV
Systolic Peak (SP) (AC)		0.1 — 300mV	12.50mV	0.01mV
Dicrotic Notch (DN)		0.1 — 300mV	7.00mV	0.01mV
Diastolic Peak (DP)		0.1 — 300mV	8.00mV	0.01mV
Lock		Lock DC: Only DC of Voltage locked	Lock DC	-
		Lock AC: AC, DN, DP of Voltage locked		
Red / Infrared (Time)				
Systolic Peak (SP) (AC)		0 — 1000ms (60BPM)	150ms	1ms
Dicrotic Notch (DN)		0 — 1000ms (60BPM)	360ms	1ms
Diastolic Peak (DP)		0 — 1000ms (60BPM)	460ms	1ms
Noise Generator (Time)				
Frequency		off / 0.5 / 1 / 2 / 3 / 5 / 10 / 25 / 50 / 60 / 100 / 120 / 1K / 5K Hz / White Noise	off	-
Amplitude		0.05 — 2.00mV	0mV	0.05mV
Respiration				
Respiration Rate		1 — 150BrPM	20BrPM	1BrPM
Inhale-Exhale Ratio		1:1, 1:2, 1:3, 1:4, 1:5	1:1	1
Wave Modulation		Baseline / Amplitude / Frequency	Baseline / Amplitude / Frequency	-
Respiration — Baseline Modulation		Variation — R: 1 — 16% Variation — IR: 1 — 16%	1% 1%	1% 1%
Respiration — Amplitude Modulation				
Respiration — Frequency Modulation				
	Duration	1 — 60s	10s	1s

Parameters		Setting Range	Default Values	Minimum Step Size
Apnea Selection	Cycle	1 – 10min	1min	1min

9.9 SpO₂ Test Mode (with Transmittance PPG Module)

Table 12: SpO₂ Test Mode Specification (with Transmittance PPG Module)

Parameters		Specifications
Heart Rate	Setting Range	10 – 300BPM
	Minimum Step Size	1BPM
	Accuracy	±1BPM
LED DC Level Reference Output	Setting Range ¹	300 – 3000mV
	Minimum Step Size	1mV
LED AC Level Reference Output	Setting Range ¹	0.1 – 300mV
	Minimum Step Size	0.01mV
PI (AC level/DC level) ²	Setting Range	0.01% – 20% (AC / DC, varies with AC or DC level)
LED1 Absolute Irradiance (100%) [§]	Intensity	2.36mW / m ² nm
	Accuracy	±10%
LED2 Absolute Irradiance (ambient light) [§]	Intensity	0.25mW / m ² nm
	Accuracy	±10%
LED Scan Rate	Rate	50 – 40kHz (Normal mode/ Standalone mode) 10kHz (Raw data mode)
	Accuracy	±5μs
PD Sample Rate	Rate	250kHz (single channel)
	Accuracy	±5μs
PD Response Time	Rising	1μs Typical ³
	Falling	1μs Typical ³
SpO ₂ (%) SpO ₂ parameter specifications ⁴	Setting Range	1% – 100%
	Minimum Step Size	1%

Parameters		Specifications
	Accuracy	91% — 100%: $\pm 1\%$ +specified accuracy of the DUT 81% — 90%: $\pm 2\%$ +specified accuracy of the DUT 71% — 80%: $\pm 3\%$ +specified accuracy of the DUT Below 70%: with unspecified accuracy

[§] Data Collection Method: To connect the spectrometer with a 2-inch integrating sphere, and fix the integrating sphere on the DUT to measure the absolute irradiance of the LED of the DUT.

Note:

1. The AECG100 test system adjusts AC/DC output according to the linearity of LED electro-optical conversion.
2. The PI value may vary according to the different calculation methods of each manufacturer.
3. PD response time varies with the light intensity of the DUT.
4. The SpO₂ parameter specifications apply to SpO₂ Test Mode.

9.10 SpO₂ Test Mode Parameters (with Transmittance PPG Module)

Table 13: SpO₂ Test Mode Parameters (with Transmittance PPG Module)

Parameters	Setting Range	Default Values	Minimum Step Size
Output Waveform	Sine / Triangle / PPG	PPG	-
BPM	10 — 300BPM	60BPM	1BPM
SpO ₂	0 — 100%	98%	1%
Red			
PI (AC level/DC level)	0.01 — 20%	2.000%	0.001%
AC	0.1 — 300mV	12.50mV	0.01mV
DC	300 — 3000mV	625mV	1mV
Output DC (offset)	0 — 2000mV	0mV	1mV
Lock	Lock AC/DC	Lock DC	-
Infrared			
PI (AC level/DC level)	0.01 — 20%	4.000%	0.001%
AC	0.1 — 300mV	25.00mV	0.01mV
DC	300 — 3000mV	625mV	1mV
Output DC (offset)	0 — 2000mV	0mV	1mV

Parameters	Setting Range	Default Values	Minimum Step Size
Lock	Lock AC/DC	Lock DC	-

9.11 Auto Test SpO₂ Test Mode Parameters (with Transmittance PPG Module)

Table 14: Auto Test SpO₂ Test Mode Parameters (with Transmittance PPG Module)

Parameters	Setting Range	Default Values	Minimum Step Size
BPM	10 — 300BPM	60BPM	1BPM
SpO ₂ *	0 — 100%	98%	1%
IR — PI	0.01% — 20%	2.4%	0.1%
Transmission Rate	Neonatal Foot Dark & Thick Finger Dark Medium Finger Normal Medium Finger Light & Medium Finger Light & Thin Finger	Normal Medium Finger	-

*Note:

SpO₂ accuracy:

91% — 100%: ±1% + specified accuracy of the DUT

81% — 90%: ±3% + specified accuracy of the DUT

71% — 80%: ±5% + specified accuracy of the DUT

Below 70%: with unspecified accuracy

9.12 General Specification

AECG100 Main Console Unit

Table 15: AECG100 Main Console Unit General Specification

Environment	Operating Temp.	10°C — 40°C
	Storage Temp.	0°C — 50°C
	Humidity	0 — 80% RH, Non-condensing
Physical Properties	Housing	Plastic
	Weight	241g
	Dimensions (L x W x H)	150mm x 98mm x 33mm

Reflectance & Transmittance PPG Module

Table 16: PPG Module General Specification

Environment	Operating Temp.	10°C – 40°C
	Storage Temp.	0°C – 50°C
	Humidity	0–80% RH, Non-condensing
Physical Properties	Housing	Plastic
	Weight	Reflectance Module: 165g Transmittance Module: 122g
	Dimensions (L x W x H)	Reflectance Module: 70mm x 98mm x 60mm Transmittance Module: 132mm x 85mm x 14mm

10 Ordering Information

AECG100 Main Console Unit

Table 17: AECG100 Main Console Unit Ordering Information

Part No.	Description	Quantity
100-AE00001	Model No.: AECG100 The main console unit for ECG testing. Supports ECG and Auto Sequence test modes.	1

PPG Modules

Table 18: PPG Module Ordering Information

Part No.	Description	Quantity
100-AE00002	Model No.: PPG-1R-525 Model Name: Reflectance Green Light Heart Rate Module The reflectance PPG module of 525nm green LED. Supports PWTT / PPG / Auto Sequence test modes.	1
100-AE00004	Model No.: PPG-2R-880 Model Name: Reflectance SpO ₂ Module The reflectance PPG module of 880nm IR LED and 660nm Red LED. Supports PWTT / SpO ₂ / PPG / Auto Sequence test modes.	1
100-AE00005	Model No.: PPG-2R-940 Model Name: Reflectance SpO ₂ Module The reflectance PPG module of 940nm IR LED and 660nm Red LED. Supports PWTT / SpO ₂ / PPG / Auto Sequence test modes.	1
100-AE00018	Model No.: PPG-2TF-660 2.0 Model Name: Transmittance SpO ₂ module (30cm) The transmittance PPG module. Supports PWTT / Auto Test SpO ₂ / SpO ₂ / PPG / Auto Sequence test modes.	1

Part No.	Description	Quantity
100-AE00025	Model No.: PPG-2TF-660 2.0 Model Name: Transmittance SpO ₂ module (60cm) The transmittance PPG module. Supports PWTT / Auto Test SpO ₂ / SpO ₂ / PPG / Auto Sequence test modes.	1

Note: Connect the AECG100 main console with the reflectance and transmittance PPG modules PPG-2R-940, PPG-2R-880 and PPG-2TF-660 2.0 can conduct SpO₂ testing as the reflectance and transmittance SpO₂ testing device.

Optional Software Add-on Pack

Table 19: Optional Software Add-on Pack Ordering Information

Part No.	Description
HA0-AE01001	Auto setup for IEC 60601-2-47:2012 performance tests.
HA0-AE01002	Auto setup for YY0885-2013 performance tests.
HA0-AE01003	Auto setup for YY 9706.247-2021 performance tests.
HCO-AE01001	To have wearables to perform more closely to medical grade device and to decrease the time and cost of clinical trials, AECG100 has built-in clinical database waveforms. All those PPG database waveforms are recorded simultaneously with ECG signals and have physicians determined the arrhythmia marks via ECG signals. The WhaleTeq database includes 30 records of PPG waveforms recorded in clinical trials to use in PPG test mode and 10 records of PPG and ECG waveforms recorded in clinical trials to use in PWTT test mode. The 25 recorded disease waveforms include symptoms such as AF (Atrial Fibrillation), APC (Atrial Premature Complexes), VPC (Ventricular Premature Contraction) and first degree AV block.
HCO-AE01002	Save Waveform Raw Data Standard waveforms in ECG, PPG, SpO ₂ and PWTT test modes can be saved in raw data formats for further modification

Optional Calibration Service and Warranty Extension

Table 20: Optional Calibration Service and Warranty Extension Ordering Information

Part No.	Description
YY0007	Model No.: C3 Provides (3) years of calibration service coverage. WhaleTeq equipment can be calibrated to original performance on the basis of (1) year interval.
YY0008	Model No.: R3 Extends the limited warranty from (1) year to (3) years.

11 Package Contents

AECG100 Test Systems

Table 21: AECG100 + PPG-1R-525 Package Contents

Part No.	Item	Quantity
100-AE00001 + 100-AE00002	AECG100 Main Console Unit	1
	PPG-1R-525 Module	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	1
	Grounding Cable (1m)	1
	RCA to BNC Cable (74cm)	2
	Compound Terminal	4
	DB15 Cable (Male to Female), 30cm	1

Table 22: AECG100 + PPG-2R-940 Package Contents

Part No.	Item	Quantity
100-AE00001 + 100-AE00005	AECG100 Main Console Unit	1
	PPG-2R-940 Module	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	2
	Grounding Cable (1m)	1
	RCA to BNC Cable (74cm)	2
	Compound Terminal	4
	DB15 Cable (Male to Female), 30cm	1

Table 23: AECG100 + PPG-2R-880 Package Contents

Part No.	Item	Quantity
	AECG100 Main Console Unit	1

100-AE00001 + 100-AE00004	PPG-2R-880 Module	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	2
	Grounding Cable (1m)	1
	RCA to BNC Cable (74cm)	2
	Compound Terminal	4
	DB15 Cable (Male to Female), 30cm	1

Table 24: AECG100 + PPG-2TF-660 2.0 Package Contents

Part No.	Item	Quantity
100-AE00001 + 100-AE00018	AECG100 Main Console Unit	1
	PPG-2TF-660 2.0 Module	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	1
	Grounding Cable (1m)	1
	USB Type-C to Type-C cable (male to male, 150cm, black)	1
	MCX (RF) Male to BNC Cable (30cm)	2
	Compound Terminal	4

AECG100 Main Console Unit and PPG Modules

Table 25: AECG100 Package Contents

Part No.	Item	Quantity
100-AE00001	AECG100 Main Console Unit	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	1
	Grounding Cable (1m)	1
	RCA to BNC Cable (74cm)	1
	Compound Terminal	4

Table 26: PPG-1R-525 Package Contents

Part No.	Item	Quantity
100-AE00002	PPG-1R-525 Module	1
	RCA to BNC Cable (74cm)	1

Table 27: PPG-2R-940 Package Contents

Part No.	Item	Quantity
100-AE00005	PPG-2R-940 Module	1
	RCA to BNC Cable (74cm)	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	1

Table 28: PPG-2R-880 Package Contents

Part No.	Item	Quantity
100-AE00004	PPG-2R-880 Module	1
	RCA to BNC Cable (74cm)	1
	USB Type-A to Type-B Cable (Male to Male), 1.8m	1

Table 29: PPG-2TF-660 2.0 (30cm) Package Contents

Part No.	Item	Quantity
100-AE00018	PPG-2TF-660 2.0 Module	1
	USB Type-C to Type-C cable (male to male, 150cm, black)	1
	MCX (RF) Male to BNC Cable (30cm)	2

Table 30: PPG-2TF-660 2.0 (60cm) Package Contents

Part No.	Item	Quantity
100-AE00025	PPG-2TF-660 2.0 Module	1
	USB Type-C to Type-C cable (male to male, 150cm, black)	1
	MCX (RF) Male to BNC cable (30cm)	2
	Signal expander module	1

Note:

1. PPG module is required to connect to AECG100 main console unit to enable PWTT / SpO₂ / PPG test modes.
2. SpO₂ test mode is only available when the reflectance PPG module or transmittance SpO₂ module is connected to AECG100 main console.

12 Revision History

Table 31: Revision History

Version	Revision Description
2019-07-24	First version
2020-07-02	- Updated cover photo - Added details to Output DC of SpO₂ mode - Added Absolute Irradiance (for PPG R/IR) under Spec Chapter - Specified file types saved for Waveform Raw/ PC file and loaded for Recall/ Player/ Auto Sequence - Added ECG ground illustration - Moved description of Setting & PPG config to a general section - SpO₂ & PPG parts: Demo figures of Sampling tab to include PD and LED switch separately

Version	Revision Description
2020-09-08	◦ Added PPG Respiration function ◦ Added Calibration section ◦ Included SAVE RAW-AECG as optional add-on software ◦ Updated SpO₂ spec (with reference DUT)
2020-10-13	◦ Updated PPG spec LED AC level
2021-01-11	◦ Moved “Resume Operation” from System Setup to Troubleshooting Chapters. ◦ Added Cautions and Revision History chapters
2021-10-01	Update ◦ Chapter 8 (point (9)) ◦ Chapter 2.3 Product Wiring Diagram ◦ Chapter 6.1 Self-calibration
2022-06-10	Updated ◦ 2.3 Product Wiring Diagram ◦ 2.4 DUT Best Position Adjustment ◦ 2.5 Operation Modes ◦ 6.1 Self-calibration ◦ Chapter 10 Ordering Information ◦ Chapter 11 Package Contents Added ◦ 4.5 Auto Test SpO₂ Mode ◦ 9.5 Transmittance PPG Module + SpO₂ Test Mode
2022-06-16	Updated ◦ 4.5 Auto Test SpO₂ Mode ◦ 9.4 Reflectance PPG Module + SpO₂ Test Mode ◦ 9.5 Transmittance PPG Module + SpO₂ Test Mode
2022-07-27	Updated ◦ 4.5 Auto Test SpO₂ Mode ◦ 4.6 SpO₂ Mode ◦ 9.1 ECG Test Mode ◦ 9.2 PPG Test Mode ◦ 9.4 Reflectance PPG Module + SpO₂ Test Mode
2022-09-12	Updated ◦ 4.6 SpO₂ Mode ◦ product name - Transmission SpO ₂ Module → Transmittance SpO ₂ Module - Reflective SpO ₂ Module → Reflectance SpO ₂ Module
2023-02-23	Updated ◦ 2.5.1 PC Software Operation ◦ 4.1 General ◦ 4.5 Auto Test SpO₂ Mode ◦ 9.4 Reflectance PPG Module + SpO₂ Test Mode

Version	Revision Description
	9.5 Transmittance PPG Module + SpO₂ Test Mode
2023-07-05	Updated 2.5.1 PC Software Operation 4.2 ECG Mode 9 Specification 10 Ordering Information 11 Package Contents Added - Subsection 4.1.1, 4.1.2, and 4.1.3
2024-01-17	Updated 4.5 Auto Test SpO₂ Mode 9.2 PPG Test Mode 9.3 PWTT Test Mode 9.4 Reflectance PPG Module + SpO₂ Test Mode 9.5 Transmittance PPG Module + SpO₂ Test Mode 10 Ordering Information 11 Package Contents
2024-04-30	Updated 1 Product Introduction
2025-03-02	Updated 4.3 PPG Mode 11 Package Contents - Figure 40, 41, 53, 54 Added 4.4.1 Download PhysioNet Database
2025-12-08	Updated 2.2 Transmittance SpO₂ module (PPG-2TF-660) 2.4.2 Transmittance SpO₂ Testing Device 4.1.1 PPG Configuration 4.1.3 Firmware Update 4.3 PPG Mode 4.5 Auto Test SpO₂ Mode 4.6 SpO₂ Mode 9 Specification 10 Ordering Information 11 Package Contents
2026-07-20	Updated 2.2 Transmittance SpO₂ module (PPG-2TF-660 2.0) 6.1 Self-calibration - Table 18: PPG Module Ordering Information Added - Table 30



WHALETEQ Co., LTD

service@whaleteq.com

+886 2 2517 6255

8F., No. 125, Songjiang Rd., Zhongshan Dist.,

Taipei City 104474, Taiwan